

Service Bulletin

SB Number:	SB 2DC-001	Issue Date: 01/07/2003
Subject:	Mistake in part no. in Service Manual (Flash DIMM)	
Model:	KM-1500	

Please be informed of the following mistake in the KM-1500 Service Manual.

PAGE 1-7-1

'Upgrading the firmware on the main PCB'

WRONG

Flash DIMM (P/N: **2BZ01180**)



CORRECT

Flash DIMM (P/N: **2DC01090**)

See [page 2](#) of this Service Bulletin for the extracted page 1-7-1 from the service manual, that contains the above mistake.

The KM-1500 service manual on our reserved website accessible via www.kmissupport.com is the revised version, that includes the correct information.

1-7-1 Upgrading the firmware on the main PCB

Firmware upgrading requires the following tools:
Flash DIMM (P/N **2BZ01180**) ! INCORRECT !

Procedure

1. Run maintenance mode U019 to check the version of the ROM.
2. Turn the power switch off and disconnect the power plug.
3. Remove the rear cover and change the jumper switch position on the main PCB to the lower side.
4. Insert the DIMM into the DIMM slot on the main PCB. Insert the power plug and turn the power switch on.
5. The upgrade operation starts and the Copy quantity/magnification display changes as follows: JIG → 1% → 99%.
6. When the upgrade operation is complete, the checksum will be displayed and a beep indicating the completion will sound.
7. Turn the power switch off and disconnect the power plug, remove the DIMM from the main PCB, and return the jumper switch to its original position. Reattach the rear cover to its original position.
8. Insert the power plug and turn the power switch on.
9. Run maintenance mode U019 to check that the version of the ROM has changed.




Figure 1-7-1