

SB Number:	SB 2DD-001	Creation Date: 17/08/2004
Subject:	How to add an optional language in FS-1018MFP?	
Model:	FS-1018MFP	

The FS-1018MFP features the addition of an extra optional language. This Service Bulletin informs you of the procedure of downloading an additional optional language to the FS-1018MFP.

The FS-1018MFP supports following 7 languages as a standard. It is possible to add 1 extra option language.


- English
- French
- Spanish
- German
- Italian
- Portuguese
- Dutch

IMPORTANT NOTE

Please mind that the addition of an optional language is supported as of firmware level **2DD_2000.002.006** and later. Please upgrade to this version or later before downloading an optional language to the FS-1018MFP!

PROCEDURE

- ❶ First format the CF card in a PC in advance.
You will need to add **2 files** to the CF card (instead of the usual 1); namely the **"VERDEF"** file and the actual option message data **"2CC_XXXXXXXXXXXX.opm"**.
Copy the data to the root directory of the CF card by using a CF WRITER.
For example (in case of Hungarian optional language):
2DD_8HU001001.opm
VERDEF
- ❷ Modify the "VERDEF" file by using a text editor to conform the file name.
Open "VERDEF" with editor. The name of the option language file should match the name mentioned in the "VERDEF" file. If not, then please change accordingly.
For example (in case of Hungarian):
VER 0.9
THIS VERDEF P
OPTMSG /2DD_81HU001001.opm B
- ❸ Insert the CF card, with the above 2 files on it, into the FS-1018MFP CF slot. *(For more details, please refer to Service Manual, Chapter 1-7-1)*
- ❹ Insert power plug again and turn power on.
- ❺ Option language file will be downloaded to machine.
While downloading, the message "Downloading" will be visible.
- ❻ When downloading is finished, the message "Completed" appears.
Turn power switch off and remove the CF card. After turning power ON again, the optional message can be selected from 'Common Settings' button => 'Language'.

 **NOTE:** Machine firmware version 2DD_2000.002.006 (or later) and the available optional language files can be downloaded from our Distributors reserved website accessible via www.kmissupport.com