

# 8

## 8. Exploded Views and Parts List

- 8.1 Main Exploded View ..... page(8-2)
- 8.2 Top Cover Exploded View ..... page(8-3)
- 8.3 OPE Ass'y Exploded View ..... page(8-4)
- 8.4 Scan Upper Ass'y Exploded View ..... page(8-5)
- 8.5 Main Frame Exploded View ..... page(8-6)
- 8.6 Fuser Unit Exploded View ..... page(8-7)
- 8.7 Exit Cover Exploded View ..... page(8-8)
- 8.8 Cassette Unit Exploded View ..... page(8-9)

- Deal drawings and service parts are declared for the items with higher rate of inferiority and replaceable in the level of service description only.
- If inferiority occurs, you can replace the parts by the unit declared in deal drawings and service items.

### Way to observe Part Code & Description

Part code and Description is quoted and controlled by determined standard. Refer to this determined standard, it will help with ordering Part.

- There are two kinds of Part code inscription type.




**Type 1** : Controlled by Company : It can be commonly used for all kinds of product SEC produce. Mostly, electronics Parts.

**Type 2** : Controlled by Division : It is used or one produce. Mostly, Mostly, mechanical Parts.

- **A/S privately used part** : It is only used for A/S .
- **Ass'y part** : Assembled by more than 2 Parts. If necessary part is not A/S Part, Ass'y part including necessary par can be used. It is shown in the diagram and drawing of SVC manual.
- Ass'y part and A/S privately used Part is distinguished by part Code and Description. The are inscription type 2. It is recognized by Part character and front side of description.


DIVISION	PART CODE	DESCRIPTION
A/S Private	**81_***** (JB81-00039A)	AS-***** (AS-USE)
ASS'Y Part	**75_***** (JB75-00068A)	MEC-***** (MEC-CHUTE)
ASS'Y Part	**92_***** (JB92-01131A)	PBA ***** (PBA MAIN-CONTROLLER)
ASS'Y Part	**97_***** (JB97-01089A)	MEA ***** (MEA UNIT-PULLEY IDLE)

# 8.1 Main Exploded View




Toner Cartridge


## 8.2 Top Cover Exploded View



### 8.3 OPE Ass'y Exploded View




## 8.4 Scan Upper Ass'y Exploded View








## 8.6 Fuser Unit Exploded View



## 8.7 Exit Cover Exploded View



# 8.8 Cassette Unit Exploded View



## Parts List(Model code : SF-565P/ETS)

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
<b>8.1 Main</b>				
8.1-1	JC96-02710A	ELA HOU-UNIT FRAME_220V;SCX-4114F,LEXM	F2074	SA
8.1-2	JC97-01854A	MEA UNIT-COVER EXIT;SF-565P,SEC,-,EXIT C	Z2408	SA
8.1-3	JC96-02733A	ELA UNIT-RX DRIVE;ML-1710/ML-1750,SAMSUN	D4033	SA
8.1-4	JC59-00018A	UNIT-HUMMINGBIRD LSU;ML-1400,-,600DPI,	L7043	SA
8.1-5	JC39-00242A	CBF HARNESS-LSU	L7002	SA
8.1-6	JC96-02976A	ELA HOU-SCAN;SF-565P,SEC,-,SCAN ,ASS'Y,-	K3030	SA
8.1-6-1	JC96-02950A	ELA HOU-COVER TOP;SF-565P,SEC,-,COVER T	-	SA
8.1-6-2	JC96-02952A	ELA HOU-OPE;SF-565P,SEC,-,OPE ASS'Y,MFP,	-	SA
8.1-8	JC97-01856A	MEA UNIT-STACKER;SF-565P,SEC,-,STACKER,A	-	SA
8.1-8-1	JC63-00324A	TRAY-M_STACKER TX A;SF-565P,ABS,2.5,240.	-	SNA
8.1-8-2	JC63-00325A	TRAY-M_STACKER TX B;SF-565P,ABS,2.5,110.	-	SNA
8.1-9	JC97-01746K	MEA UNIT-COVER FRONT;SF-565P,SEC,-,OPEN	Z2409	SA
8.1-9-1	JC70-00303F	ADJUST-M_MANUAL R;SF-565P,HIPS,2.5,33.9,	K2009	SA
8.1-9-2	JC70-00304A	ADJUST RACK-M-MANUAL;ML-1400,POM(M90-4	K2007	SA
8.1-9-3	JC63-00103H	COVER-M_FRONT;SF-565P,HIPS,2.5,320.6,157	-	SNA
8.1-9-4	JC70-00302F	ADJUST-M_MANUAL L;SF-565P,HIPS,2.5,33.9,	K2008	SA
8.1-9-5	JC66-00387A	GEAR-RACK_PINION;ML-1400,POM(M90-44),-,-	G0378	SA
8.1-10	JC63-00320A	COVER-M_SIDE R;SF-565P,HIPS,2.5,290.0,26	-	SA
8.1-11	JC96-02974A	ELA HOU-COVER SIDE L;SF-565P,SEC,-,SIDE	Z2269	SA
8.1-11-1	JC63-00319A	COVER-M_SIDE L;SF-565P,HIPS,2.5,290.0,26	-	SNA
8.1-11-2	3001-001494	SPEAKER;1W,8OHM,83DB,500HZ	-	SA
8.1-11-3	GB70-10500A	IPR-UNIT FIXING BRAC	-	SNA
8.1-12	JC97-01855A	MEA UNIT-COVER REAR;SF-565P,SEC,-,COVER	Z2421	SA
8.1-12-1	JC63-00321A	COVER-M_REAR;SF-565P,HIPS,2.5,320.0,280.	-	SNA
8.1-12-2	JC63-00142D	COVER-M_FACE UP;SF-565P,ABS,2.5,244.6,85	Z2142	SA
8.1-13	JC31-00027A	FAN-DC HUMMINGBIRD	F5019	SA
8.1-14-1	JC66-00528A	ROLLER-TRANSFER ROLLER;ML-1510,NBR+EC	T3014	SA
8.1-14-2	JC72-00851A	PPR-SPACER TR	-	SNA
8.1-14-3	JC66-00395A	GEAR-TRANSFER;ML-1400,POM(M90-44),-,-,-,	G0448	SA
8.1-15	JC97-01750E	MEA UNIT-CASSETTE;SF-565P,SEC,-,CASSETT	C4016	SA
8.1-16	JC96-02813A	ELA HOU-FUSER 220V, ROCKY;SCX-4114F,SEC	F4002	SA
8.1-17	JC97-01794A	MEA UNIT-SHIELD ENGINE;SCX-4114F,SAMSUN	E2098	SA
8.1-17-1	JC63-00144A	SHIELD-ENGINE, ROCKY;SCX-4114F,SECC,T0.8	E2107	SA
8.1-17-2	6103-001056	SUPPORTER;DASC-8N,L11,NATUAL,NYLON 6/6	-	SNA
8.1-18	JC61-00693A	BRACKET-P-INLET, ROCKY;SCX-4114F,SECC,T	B4027	SA
8.1-19	JC44-00063A	SMPS-POWER PBA(V2)_CHINA;SF-565P,*,AC/DC	M0466	SA
8.1-20	JC39-00240B	CBF HARNESS-ENGINE	H1070	SA
8.1-21	JC92-01576A	PBA MAIN-NIKE2_LOW;SF-565P,USA,USA,16PP	M0232	SA
8.1-22	JC92-01578B	PBA SUB-NIKE2_LOW(EU);SF-565P,SEC,EU,LIU	L5106	SA
8.1-23	JC39-00317A	CBF SIGNAL-LIU FFC	-	SNA
8.1-24	6103-001048	SUPPORTER;DASS-T20N,L37.1,NTR,NYLON6/6	-	SA
8.1-25	JC97-01858A	MEA UNIT-CRADLE;SF-565P,SEC,-,CRADLE,ASS	K3553	SA
8.1-26	JC96-01629F	ELA HOU-HANDSET;SF-565P,SEC,UK,HANDSET	H0009	SA
8.1-27	JC92-01570A	PBA SUB-HOOK;SF-565P,USA,USA,HOOK PBA,-	-	SA
8.1-28	JC39-00311A	CBF HARNESS-HOOK;SF-565P,WIRE HARNESS	-	SNA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
<b>8.2 Top Cover</b>				
8.2-0	JC96-02950A	ELA HOU-COVER TOP;SF-565P,SEC,-,COVER T	-	SA
8.2-1	JC63-00323A	COVER-M_TOP;SF-565P,HIPS,2.5,286.2,356.2	-	SA
8.2-2	JC72-00973A	PMO-STACKER_RX;ML-1400,ABS,BLUE,-,V0,-	Z5090	SA
8.2-3	JC96-02949A	ELA HOU-SCAN MOTOR;SF-565P,SEC,-,SCAN M	M2166	SA
8.2-4	JC31-00032A	MOTOR STEP-TX;SP-42HD-120M,SF-565P,0.2A,	M2166	SA
8.2-5-1	JC66-00680A	SHAFT-M_DRIVER ADF;SF-565P,ACETAL,98.1,5	-	SNA
8.2-5-2	JB72-00136A	PMO-SLEEVE ADF;SF-3100,POM,NTR,9	-	SNA
8.2-5-3	JB75-00052A	MEC-ROLLER ADF;SF-3100,SEUK,NTR	A2013	SA
8.2-6	JC72-00387A	PMO-BUSHING_F/DOWN;ML-6060A,POM,BLK,-,-	K3854	SA
8.2-7	JC61-00865A	PLATE-P_GROUND CIS;SF-565P,PHOSPHOR BF	-	SNA
8.2-8	6107-001224	SPRING-TS;SUS304WPB,-,PI0.95,-,-,-,ID6	-	SA
8.2-9	JG72-40744A	PMO-BUSHING TX(B4);CF5700,POM,NTR+WHT(	-	SA
8.2-10	JB66-00204A	SHAFT-M_EXIT 21;SF-452,POM,-,14,-,-,-	S4113	SA
8.2-11	JC66-00681A	LINK-M_SCAN OPEN;SF-565P,ACETAL,59.2,2.5	-	SNA
8.2-12	JC61-00858A	GUIDE-M_DOC L;SF-565P,HIPS,2.5,126.8,38.	-	SA
8.2-13	JC61-00859A	GUIDE-M_DOC R;SF-565P,HIPS,2.5,126.8,38.	-	SA
8.2-14	JB66-00126A	GEAR-PINION SSI;MJC-3700,POM,0.7,18,12.6	-	SNA
8.2-15	JB75-00053A	MEC-ROLLER WHITE;SF-3100,SEUK,WH	-	SNA
8.2-16	JC72-41191A	PMO-BEARING SHAFT;ML-6000,POM,WHT,HB,-	S4068	SA
8.2-17	0609-001174	CONTACT IMAGE SENSOR	-	SA
8.2-18	JB61-00138A	GUIDE-M_CIS L;SF-330,POM,T1.5,W44,L32.5,	G2308	SA
8.2-19	JB61-00137A	GUIDE-M_CIS R;SF-330,POM,T1.5,W44,L32.5,	G2309	SA
8.2-20	JB61-70938A	SPRING-CIS(ATLAS);SF3000,SUS304W	L5001	SA
8.2-21	JC97-01865A	MEA UNIT-CHUTE;SF-565P,SEC,-,CHUTE ASS'Y	-	SA
8.2-21-1	JC61-00860A	CHUTE-M_A;SF-565P,HIPS,IVORY,106.2,-,2.5	-	SNA
8.2-21-2	JC61-00861A	CHUTE-M_B;SF-565P,HIPS,IVORY,106.0,-,2.5	-	SNA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
<b>8.3 OPE Ass'y</b>				
8.3-0	JC96-02952A	ELA HOU-OPE;SF-565P,SEC,-,OPE ASS'Y,MFP,	-	SA
8.3-1	JC63-00326A	COVER-M_OPE;SF-565P,HIPS,2.5,272.5,136.0	-	SNA
8.3-2	JC72-00672A	PCT-LCD WINDOW;SF-535E,PC SHEET T0.38,-,	-	SNA
8.3-3	JC63-00328A	SHEET-ONE TOUCH;SF-565P,PC SHEET,T0.38,5	-	SNA
8.3-4	JC68-01221A	LABEL(P)-ONE TOUCH;SF-565P,SEC,ART 120G,	-	SNA
8.3-5	JC64-00113A	KEY-M_ONE TOUCH;SF-565P,HIPS,59.0*84.0*1	-	SNA
8.3-6	JC64-00112A	KEY-M_COPY;SF-565P,HIPS,16*79.0*19.0,HB,	-	SNA
8.3-7	JB72-00107B	PMO-KEY STOP;SF-3100,HIPS,ICE ORANGE,PI	K0216	SA
8.3-8	JC64-00114A	KEY-M_START;SF-565P,HIPS,D29.0,HB,IVORY,	-	SNA
8.3-9	JC64-00056A	KEY-M-SCROLL;SCX-4114F,HIPS,-,HB,IV21,-,	K0050	SA
8.3-10	JC64-00053A	KEY-M-TEL;SCX-4114F,HIPS,-,HB,IV21,-,-	K0062	SA
8.3-11	JC64-00058A	KEY-M-TONER SAVE;SCX-4114F,ACRYL,-,HB,CL	K0068	SNA
8.3-12	JC64-00060A	KEY-M-FAX;SCX-4114F,HIPS,-,HB,IV21,-,-	K0038	SA
8.3-13	JC64-00115A	KEY-M_SHIFT;SF-565P,HIPS,D14.0,HB,IVORY,	-	SNA
8.3-14	JC73-00172A	RUBBER-ONE TOUCH;SF-565P,SILICON,99.0*89	-	SNA
8.3-15	JC73-00171A	RUBBER-TEL;SF-565P,SILICON,159.0*104.0,-	-	SNA
8.3-16	JC92-01558A	PBA SUB-LOW_OPE;SF-565P,SEC,KOREA,OPE,	-	SA
8.3-17	JC39-00310A	CBF HARNESS-OPE;SF-565P,WIRE HARNESS,U	-	SNA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
<b>8.4 Scan Upper Ass'y</b>				
8.4-0	JC97-01857A	MEA UNIT-SCAN UPPER;SF-565P,SEC,-,SCAN U	-	SA
8.4-1	JC61-00864A	FRAME-M_SCAN UPPER;SF-565P,HIPS,-,HB,IVC	-	SA
8.4-2	JC72-41398A	PMO-LOCKER_MP;ML-6100,POM,NTR,V0,-	L6048	SA
8.4-3	JC39-00319A	CBF HARNESS-SCAN GND;SF-565P,-,UL1007,-,	-	SNA
8.4-4	JB61-00107A	OPRING ETC-LEVER SENSOR;SF-430,SUS304,0	Z4209	SA
8.4-5	JB66-00219A	LEVER-M_SENSOR DOC;SF-452,ABS,1.6,18.1,2	S3060	SA
8.4-6	JB61-00084A	SPRING ETC-ADF;SF-4755,SEP-B,##0.4,##3.0	Z4134	SA
8.4-7	JC72-41398A	PMO-LOCKER_MP;ML-6100,POM,NTR,V0,-	L6048	SA
8.4-8	JG72-40043A	PMO-SUPPORT ADF;SF4000,POM,WHT,V	Z7018	SA
8.4-9	JC66-00558A	SHAFT-IDLE FEED;SCX-4114F,SUM24L,60,2.5,	F6212	SA
8.4-10	JG72-40663A	PMO-ROLL PINCH;SF5500,POM,BLK,HB,-	P4013	SA
8.4-11	JC73-00032A	RPR-RUBBER ADF;SF-5100,SILICON,28.6*39.2	K4249	SA
8.4-12	JG72-40044A	PMO-HOLDER RUBBER;SF4000,POM,WHT	H4107	SA
8.4-13	JC67-00055A	BRUSH-ANTISTATIC 531P;SF-531P,AL+THUNDE	-	SA
8.4-14	JC61-70911A	SPRING ETC-EXIT ROLL FD;ML-165,SUS304 WF	-	SA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
<b>8.5 Main Frame</b>				
8.5-0	JC96-02710A	ELA HOU-UNIT FRAME_220V;SCX-4114F,LEXM	F2074	SA
8.5-1	JC61-00579A	FRAME-M-BASE;ML-1400,VBS(VH-0810P),-,B	B0080	SA
8.5-2	JC61-00607A	GUIDE-P-TR ;ML-1400,SECC,0.5,241,95,-,-	G2089	SA
8.5-3	JC61-00604A	PLATE-P-SAW;ML-1400,SUS304-CSP,0.15,16,2	P5152	SNA
8.5-4	JC61-00594A	GUIDE-M-TR RIB;ML-1400,PC+ABS,-,-,BLK,	G2079	SA
8.5-5	JC72-00143A	PMO-GEAR_EXIT_DRV16;SF-5100,POM,	-	SNA
8.5-6	6044-000001	RING-CS;ID3,OD3,T0.25,BLACK,SUS304	-	SNA
8.5-7	JC61-00836A	FOOT-FRONT;ML-1750,NBR,D7,-,12,-,-	F1011	SA
8.5-8	JC70-00311A	IPR-P-GROUND_TR;ML-1400,SUS304-CSP,-,0.2	F4104	SNA
8.5-9	JC75-00049A	MEC-TERMINAL;SF-5100,SAMSUNG,IVR	K3739	SA
8.5-10	JC70-00312A	IPR-P-TERMINAL CON;ML-1400,SUS304-CSP,-,	K3385	SA
8.5-11	JC70-00313A	IPR-P-TERMINAL CR;ML-1400,SUS304-CSP,-,0	K3386	SA
8.5-12	JC61-00592A	HOUSING-TERMINAL;ML-1400,ABS,-,-,BLK,V	H6040	SA
8.5-13	JC72-00983A	PMO-LOCKER CST;ML-1400,POM,BLK,-,-,-,-	L6030	SA
8.5-14	JC72-00974A	PMO-ACTUATOR CVR OPEN;ML-1400,ABS,BLK,	O1073	SA
8.5-15	JC72-00985A	PMO-PLATE GUIDE DEVE_R;ML-1400,POM(M90	G2286	SA
8.5-16	JC61-70932A	SPRING ETC-GUIDE DEVE;ML-5000A,-,D4.5,-,	Z4188	SA
8.5-17	JC70-00458A	IPR-P-GROUND_GUIDE PAPER;ML-1710,SUS30	G2285	SNA
8.5-18	JC72-00984A	PMO-PLATE GUIDE DEVE_L;ML-1400,POM(M90-	G2285	SA
8.5-19	JC72-00976A	PMO-ACTUATOR FEED;ML-1400,ABS,BLK,-,-,HB	F6156	SA
8.5-20	JC72-00975A	PMO-ACTUATOR EMPTY;ML-1400,ABS,BLK,-,-,H	K3816	SA
8.5-21	JC72-00977A	PMO-ACTUATOR MANUAL;ML-1400,ABS,BLK,-,-	K3817	SA
8.5-22	JC70-00307A	IPR-P-EARTH TRANSFER;ML-1400,SECC,-,1.0T	K3367	SA
8.5-23	6107-001162	SPRING-ETC;SUS304-WPB,-,PI0.45,D4.45,L12	-	SA
8.5-24	JC66-00526A	ROLLER-FEED ROLLER 1;ML-1510,SUM24L+EP	F6201	SA
8.5-25	JC72-00382B	PMO-BUSHING FEED;ML-1710,DELRI8903,WH	F6161	SA
8.5-26	JC66-00398A	SHAFT-FEED;ML-1400,POM+GF20%,-,-,-,-	F6210	SA
8.5-27-1	JC61-00586A	BUSH-M-PICK_UP L	P2039	SA
8.5-27-2	JC66-00399A	SHAFT-P-PICK_UP;ML-1400,SECC,-,-,-,0.8	P2160	SA
8.5-27-3	JC61-00593A	STOPPER-PICK_UP;ML-1400,POM(M90-44),-,-,	-	SNA
8.5-27-4	JC72-00982A	PMO-IDLE PICK_UP;ML-1400,POM(M90-44),NTR	P2131	SNA
8.5-27-5	JC72-01231A	SPONGE-ROLLER PICK_UP;ML-1510,URETHAN	P2164	SA
8.5-27-6	JC61-00587A	BUSH-M-PICK_UP R;ML-1400,POM(M90-44),-,-	P2067	SA
8.5-27-7	JC61-00591A	HOUSING-M-PICK_UP;ML-1400,PC+ABS,-,-,N	P2040	SA
8.5-28	JC70-00307A	IPR-P-EARTH TRANSFER;ML-1400,SECC,-,1.0T	K3367	SA
8.5-29	JC61-00583A	HOLDER-PTL;ML-1400,ABS,-,-,BLK,-	H4041	SA
8.5-30	JC67-00027A	LENS-PTL;ML-1400,PC,NTR,-,-,-,-	K3433	SA
8.5-31	JC61-00588A	BUSH-M-TR L;ML-1400,POM(M90-44),-,-,BL	K2886	SA
8.5-32	JC61-00047A	SPRING ETC-TR L HAWK;ML-6060A,SUS 304 WP		SA
8.5-33	JC66-00598A	ROLLER-FEED ;ML-1710,SUM24L+EPDN,3/14.5,	F6200	SA
8.5-34	JC72-00102A	PMO-BUSHING_TR(L);SF-5100,POM ,B	K3856	SA
8.5-35	JC70-00310A	IPR-P-GROUND_FUSER;ML-1400,SUS304-CSP,-	F4105	SNA
8.5-36	JC66-00527A	SHAFT-FEED IDLE;ML-1510,SUM24L,225,8,-,-	F6209	SA
8.5-37	JC61-00585A	BUSH-M-FEED IDLE;ML-1400,POM(M90-44),-,-	F6043	SA
8.5-38	JC61-70958A	SPRING ETC-TR	Z4041	SNA
8.5-39	JC70-00335A	IPR-P_GROUND_DRIVE2;ML-1400,SUS304-CSP	D4060	SA
8.5-40	6107-001170	SPRING-TS	-	SA
8.5-41	JC66-00377A	CAM-M-PICK_UP;ML-1400,POM(M90-44),-,-,NT	P2042	SA
8.5-42	JC70-00308A	IPR-P-GROUND_DRIVE;ML-1400,SUS304-CSP,-,	F4106	SNA
8.5-43	JC33-00009A	SOLENOID-HB (PICK-UP);-,ML-1510,DC24V,-,	P2162	SA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
8.5-44	JC33-00010A	SOLENOID-HB (MANUAL);-,ML-1510,DC24V,-,-	S8014	SA
8.5-45-1	JC72-00980A	PMO-GEAR PICK_UP B;ML-1400,POM(M90-44),N	P2126	SA
8.5-45-2	JC72-00979A	PMO-GEAR PICK_UP A;ML-1400,POM(M90-44),N	P6221	SA
8.5-45-3	6107-001167	SPRING-CS	-	SA
<b>8.5 Main Frame (contined.)</b>				
8.5-46	JC61-00602A	BRACKET-P-FEED;ML-1400,SECC,1,-,-,-,-	F6040	SA
8.5-47	JC97-01788A	MEA UNIT-CLUTCH;ML-1710,SAMSUNG,-,-,-,-,-	C9040	SA
8.5-47-1	JC66-00393A	GEAR-FEED 1;ML-1400,POM(M90-44),-,-,-,NT	F6071	SA
8.5-47-2	JC72-00978A	PMO-COLLAR_SPRING;ML-1400,POM(M90-44),N	Z4125	SA
8.5-47-3	6107-001170	SPRING-TS	-	SA
8.5-47-4	JC72-00981A	PMO-HUB CLUTCH;ML-1400,POM(M90-44),NTR,	-	SNA
8.5-47-5	JC66-00398A	SHAFT-FEED;ML-1400,POM+GF20%,-,-,-,-,-	F6210	SA
8.5-48	JC96-02813A	ELA HOU-FUSER 220V, ROCKY;SCX-4114F,SEC	F4002	SA
8.5-49	JC61-00718A	GUIDE-P-PAPER;ML-1710,SECC,0.8,24.9,262.	G2086	SA
8.5-50	JC66-00394A	GEAR-FEED 2;ML-1400,POM(M90-44),-,-,-,NT	F6072	SA
8.5-51	JC66-00396A	GEAR-IDLE 23;ML-1400,POM(M90-44),0.8,23,	G0256	SA
8.5-52	6107-001164	SPRING-TS	-	SA
8.5-53	6107-001165	SPRING-TS	-	SNA
8.5-54	JC70-00340A	IPR-P-TERMINAL DEVE KEY;SCX-4114F,SUS304	T2116	SNA
8.5-55	JC39-00229A	CBF HARNESS-OPC_FUSE;SCX-5312F,WIRE HA	H0023	SA
8.5-56	JC92-01620B	PBA SUB-PTL;SCX-4100,SEC,-,PTL,-,-,-,9.5	M0248	SA
8.5-57	JC61-00937A	GUIDE KNOCK UP	P5146	SA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
<b>8.6 Fuser Unit</b>				
8.6-0	JC96-02813A	ELA HOU-FUSER 220V, ROCKY;SCX-4114F,SEC	F4002	SA
8.6-1	JC63-00105A	COVER-M-FUSER;ML-1400,PET+GF30%,,-,-,V0	-	SNA
8.6-2	JC61-00584A	HOLDER-M-PLATE CLAW;ML-1400,PET+GF30%	-	SA
8.6-3	JC61-00064A	SPRING-CLAW;ML-5200A,SUS 304 WPB	-	SNA
8.6-4	JC72-40361A	PMO-ROLLER_EXIT;SCF(XR),POM,NTR,-,-	R0015	SNA
8.6-5	JC61-70976A	SPRING ETC-FUSER EXIT;-,-,SUS304WPB,D2.8,-	S0021	SNA
8.6-6	JC47-00005A	THERMOSTAT-150;ML-1510,-,125/250V,15/7.5	K4279	SA
8.6-7	JC72-00143A	PMO-GEAR_EXIT_DRV16;SF-5100,POM,	-	SNA
8.6-8	JC66-00396A	GEAR-IDLE 23;ML-1400,POM(M90-44),0.8,23,	G0256	SA
8.6-9	6044-000001	RING-CS;ID3,OD3,T0.25,BLACK,SUS304	-	SNA
8.6-10	JC66-00397A	GEAR-RDCN 25/15;ML-1400,POM(M90-44),-,25	G0386	SA
8.6-11	JC70-00466A	ELECTRODE-LAMP2;ML-1750 / ML-1710,-,2,-,	-	SNA
8.6-12	JC70-00450A	ELECTRODE-WIRE L;ML-1510,-,-,-,-,-	-	SA
8.6-13	1404-001298	HERMISTOR-NTC;7KOHM,-,3370K,0.3MW/C,-,-	W3071	SA
8.6-14	JC70-00449A	ELECTRODE-WIRE R;ML-1510,-,-,-,-,-	-	SA
8.6-15	JC39-00238A	CBF HARNESS-FUSER 220V;ML-1710,UL3122 #1	H1087	SA
8.6-16	JC66-00564A	GEAR-FUSER, Z37;ML-1710,HTN51G35HSL,0.8,	-	SA
8.6-17	JC61-00589A	BUSH-M-HR L;ML-1400,PPS,-,-,-,-,V0	-	SNA
8.6-18	JC66-00601A	ROLLER-HEAT	H2010	SA
8.6-19	JC61-00590A	BUSH-M-HR R;ML-1400,PPS(RBA313N, CONDU	-	SA
8.6-20	4713-001183	LAMP-HALOGEN	K2297	SA
8.6-21	JC66-00380A	ROLLER-M-EXIT F/UP;ML-1400,PC(NH-1023),1	E4159	SA
8.6-22	JC66-00600A	ROLLER-PRESSURE	P6014	SA
8.6-23	JC66-10901A	BEARING-PRESSURE/R;ML-165,PPS,5,-,14.8	-	SA
8.6-24	6107-001168	SPRING-CS	-	SNA
8.6-25	JC72-00382A	PMO-BUSHING TX;ML-6060A,POM,BLK,-,-	-	SNA
8.6-26	JC61-00581A	HOLDER-ACTUATOR;ML-1400,PC(NH-1023),-,	-	SNA
8.6-27	JC72-00987A	PMO-ACTUATOR_EXIT;ML-1400,PC(NH-1023),BL	E4093	SA
8.6-28	JC70-00317A	IPR-P-FRAME_FUSER;ML-1400,SECC,-,1.2,356	-	SNA
8.6-29	JC61-00595A	GUIDE-M-INPUT;ML-1400,PET+GF30%,,-,-,BL	-	SNA
8.6-30	6107-001165	SPRING-TS	-	SNA
8.6-31	JC73-00017A	RMO-RUBBER_EXIT;SF-5100,EPDM,11.	-	SA
8.6-32	6021-000222	NUT-HEXAGON;2C,M3,ZPC(YEL),SM20C,-	M0006	SNA
8.6-33	JC68-30928D	LABEL(P)-CAUTION, HOT_FUSER	L0035	SNA
8.6-34	JC63-00244A	COVER-M-EXIT LOWER;ML-1750,PET GF 30%,-,	-	SNA
8.6-35	JC61-00605A	PLATE-P-CLAW;ML-1400,SUS304-CSP,0.1,-,-,	-	SNA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
<b>8.7 Exit Cover</b>				
8.7-0	JC97-01854A	MEA UNIT-COVER EXIT;SF-565P,SEC,-,EXIT C	Z2408	SA
8.7-1	JC63-00322A	COVER-M_EXIT;SF-565P,HIPS,2.5,330.0,135.	-	SNA
8.7-2	JC66-00378A	ROLLER-EXIT F/DOWN;ML-1400,PC(NH-1023),1	E4159	SA
8.7-3	JC73-40915A	RMO-RUBBER EXIT	E4155	SA
8.7-4	JC66-00626A	ROLLER-M_DECURL;SCX-4114F,POM,D14.4,-,W	K4219	SA
8.7-6	JC61-00829A	HOLDER-BEARING EXIT F/DOWN;SCX-4216F,PC	H4009	SA
8.7-7	JC66-00038A	GEAR-EXIT F/DOWN;ML-4500,POM,WHT	E4039	SA
8.7-8	JC66-10201A	BEARING-EXIT FU;ML-80,POM,-,-,-	B1015	SA
8.7-9	JC61-00829A	HOLDER-BEARING EXIT F/DOWN;SCX-4216F,PC	H4009	SA
8.7-10	JC72-41081B	PMO-M-ROLLER EXIT_MAIN 5;ML-1710,POM, 50	-	SNA
8.7-11	JC72-41082B	PMO-M-ROLLER EXIT_FR 500;ML-1710,POM, 50	-	SNA
8.7-12	6107-001163	SPRING-CS;SUS304-WPB,-,PI0.4,D3.9,L13,-,	-	SA
8.7-13	JC72-00143A	PMO-GEAR_EXIT_DRV16;SF-5100,POM,	-	SNA
8.7-14	6044-000001	RING-CS;ID3,OD3,T0.25,BLACK,SUS304	-	SNA
8.7-15	JC66-00396A	GEAR-IDLE 23;ML-1400,POM(M90-44),0.8,23,	G0256	SA
<b>8.8 Cassette Unit</b>				
8.8-0	JC97-01750E	MEA UNIT-CASSETTE;SF-565P,SEC,-,CASSETT	C4016	SA
8.8-1	JC61-00578D	FRAME-M_CASSETTE;ML-1710/XRX,HIPS(HR-13	C4008	SA
8.8-2	JC61-00918B	GUIDE-M-EXTENSION L2;ML-2250,HIPS,-,150,	E5013	SNA
8.8-3	JC72-00971A	PMO-EXTENSION SMALL;ML-1400,HIPS(HR-136	E5014	SA
8.8-4	JC61-00603A	PLATE-P-KNOCK_UP;ML-1400,SECC,1,282,162,	-	SNA
8.8-5	6107-001166	SPRING-CS	-	SA
8.8-6	JC61-00580A	HOLDER-M-PAD;ML-1400,PC(NH-1023),-,-,-	H4029	SA
8.8-7	JC61-70911A	SPRING ETC-EXIT ROLL FD;ML-165,SUS304 WF	-	SA
8.8-8	JC66-00529A	ROLLER-M-IDLE FEED;ML-1510,POM,13,13,-,-	F6203	SA
8.8-9	6107-001047	SPRING-ES;PI0.45,D2.75,L24.2,-,SUS304	-	SA
8.8-10	JC72-00972A	PMO-PLATE_LOCKER;ML-1400,POM(M90-44),W	L6051	SA
8.8-11	JG61-70531A	SPRING ETC-LOCKER,PLATE	Z4215	SA
8.8-12	JC70-00300A	ADJUST-M-CASSETTE_L;ML-1400,ABS,-,-,-,BL	K2014	SA
8.8-13	JC70-00301A	ADJUST-M-CASSETTE_R;ML-1400,ABS,-,-,-,BL	K2015	SA
8.8-14	JG66-40003A	GEAR-PINION;SF4000,POM,WHT,M1,Z1	G0369	SA
8.8-15	JC64-00040F	INDICATOR-M_LEVER;SF-565P,HIPS,-,GRAY,HB	L4029	SA
8.8-16	JC73-00140A	RPR-FRICTION PAD;ML-1510,NBB,1T 10*45,60	P0034	SA
8.8-17	JC70-00314A	IPR-PLATE PAD;ML-1400,SUS304-CSP,-,0.1,-	P0009	SA
8.8-18	JC73-00141A	RPR-PAD CASSETTE;ML-1510,NBB,1T 10*45,52	-	SNA

## Pull Parts List (Reference SVC-BOM)

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
-	JC96-02707D	ELA-TONER UNIT SEE;SCX-4216F,SEC,EUROPE	-	SNA
-	JC02-00005A	TONER-POLYESTER CLEANLESS;ML-450	-	SNA
-	JC61-00782A	FRAME-M_DEV UPPER_SAMSUNG;ML-1710,HIF	-	SNA
-	JC68-01040A	MANUAL-CARD PROTECTION;ML-1710,SEC,-,-,-	-	SNA
-	JC71-00034B	NEX-OPC DRUM 1710 MITSU;-;ML-1710,A5003,	-	SNA
-	JC97-01696A	MEA ETC-DEVE;ML-1710/1750,SAMSUNG,-,-,-,	-	SNA
-	0105-001032	PAPER-ART;75g,W210,-,WHITE,HANSO	-	SNA
-	0201-001162	ADHESIVE-CYA;LOCTITE403,NTR,1250	-	SNA
-	0201-001183	ADHESIVE-AA;ARON ALPHA #202F,NTR,100,200	-	SNA
-	0203-001189	TAPE-ACETATE;#810,T0.05,W12,L65000,NTR	-	SNA
-	0205-001059	GREASE-BEARING;PETAMO GHV 133,BE	-	SNA
-	0205-001067	GREASE-GRAPHITE;NYOGEL 756G,HYDR	-	SNA
-	0205-001088	GREASE-BEARING;HANARL FL-955,NOISE DAM	-	SNA
-	6003-000119	SCREW-TAPTITE	-	SA
-	6031-000019	WASHER-PLAIN;-;ID6.1,OD8.5,T0.1,	-	SNA
-	6031-000022	WASHER-PLAIN	-	SNA
-	6031-000023	WASHER-PLAIN;-;ID5.9,OD10.0,T0.5	-	SNA
-	6031-001051	WASHER-PLAIN;M4,ID4.1,OD7.0,T0.1	-	SNA
-	JC61-00025A	SPRING-CS-CHARGE APOLLO;SF-5100,	-	SNA
-	JC61-00063A	SUPPORT-SEAL;ML-7000,EPDM SPONGE,T1.0,8	-	SNA
-	JC61-00608A	FRAME-M-DEV LOWER;ML-1400,ABS,-,-,-,2.2,	-	SNA
-	JC61-00610A	PLATE-M-DEV L;ML-1400,ABS,2,-,-,-,104*36	-	SNA
-	JC61-00611A	PLATE-M-DEV R;ML-1400,ABS,2,-,-,-,104*36	-	SNA
-	JC62-00083A	SEAL-SUPPLY L;ML-1510,PORON,-,T5.0,47,28	-	SNA
-	JC62-00084A	SEAL-SUPPLY R;ML-1510,PORON,-,T5.0,47,28	-	SNA
-	JC62-00085A	SEAL-SIDE;ML-1510,URETHAN FORM ,-;T3.5,8	-	SNA
-	JC62-00086A	SEAL-SIDE CAP;ML-1510,EPDM,-,-,-,-,HARDN	-	SNA
-	JC62-00090A	SEAL-FRAME LOWER;ML-1710,URETHAN FORM	-	SNA
-	JC66-00381A	GEAR-AGITATOR;ML-1400,POM,0.6,22,-,-,-,-	-	SA
-	JC66-00382A	GEAR-IDLE 26/13;ML-1400,POM,0.6,26/13,-,	-	SA
-	JC66-00383A	GEAR-IDLE 17/22;ML-1400,POM,0.8/0.6,17/2	-	SA
-	JC66-00384A	GEAR-DEVE ROLLER;ML-1400,DELIN 500CL,0.8	-	SA
-	JC66-00385A	GEAR-SUPPLY ROLLER;ML-1400,DELIN 500CL,0	-	SA
-	JC66-00386A	GEAR-OPC L;ML-1400,POM,0.6,30,6.3 / 10,-	-	SA
-	JC66-00522A	ROLLER-SUPPLY ROLLER;ML-1510,-,11.3,218,	-	SNA
-	JC66-00523A	ROLLER-DEVE ROLLER;ML-1510,NBR+ECO,14,2	-	SNA
-	JC67-00028A	CAP-M-DEV L;ML-1400,ABS,2,-,-,-,19*27*2.	-	SNA
-	JC67-00029A	CAP-M-DEV R;ML-1400,ABS,2,-,-,-,19*27*2.	-	SNA
-	JC68-00274A	LABEL(R)-RIBBON;SF-5100,100,-,-,	-	SNA
-	JC68-10914D	LABEL(P)-SERIAL NO;ML-85,ART,70X	-	SNA
-	JC69-00078A	BAG-DEVE APOLLO;SF-5100,CONDUTIV	-	SNA
-	JC70-00153A	IPR-ELECTRODE CHARGE;ML-4500,SUS	-	SNA
-	JC70-00305A	ELECTRODE-P-SR;ML-1400,-,-,-,-,-	-	SNA
-	JC70-40910A	ICT-SHAFT GEAR;MLE-5000,SUM24L,-,-	-	SNA
-	JC70-50901A	IPM-BUSHING DEV R;MLE-5000,BRONZ	-	SNA
-	JC72-00082A	PMO-BUSHING AGI R;SF-5100,POM,WH	-	SNA
-	JC72-00083A	PMO-HOLDER CR L;SF-5100,POM(C20)	-	SNA
-	JC72-00288A	PPR-SPACER DR;SF-5100,PET FILM,	-	SNA
-	JC72-00288B	PPR-SPACER DR R;SF-5100,TETRON,W	-	SNA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
-	JC72-00289B	PPR-FILM REAR APO;SF-5100,PET FI	-	SNA
-	JC72-40232A	PMO-CAP AGITATOR;ML-80,PP,BLK,-,	-	SNA
-	JC72-40332A	PMO-BUSHING_CHARGE;ML-80,POM,BLK	-	SNA
-	JC72-41105A	PMO-BUSHING DEV;MLE-5000,POM,NTR,-,-	-	SNA
-	JC73-00021A	RPR-SEAL BLADE;SF-5100,URETHANE	-	SNA
-	JC73-00055A	RPR-SEAL SPACE	-	SNA
-	JC73-10017A	RPR-SEAL_BLOCK;ML-80,URETHANE_FOAM,T3	-	SNA
-	JC73-10914A	RPR-SEAL FILM;MLE-5000,URETHANE	-	SNA
-	JC75-00043A	MEC-GEAR OPC R;SF-5100,SEC,POM+C	-	SNA
-	JC66-00012A	GEAR-OPC R;SF-5100,POM(M90-44),B	-	SNA
-	JC71-00002A	NPR-EARTH OPC APOLLO;SF-5100,C52	-	SNA
-	JC75-00044A	MEC-BUSHING AGI L;SF-5100,SEC,PO	-	SNA
-	JC72-00081A	PMO-BUSHING AGI L;SF-5100,POM,WH	-	SNA
-	JC73-40906A	RMO-SEAL AGITATOR;MLE-5000,SANTO	-	SNA
-	JC75-10973C	MEC-AGITATOR;SF-5100,SEC,ABS+PET	B1030	SNA
-	JC72-10924A	PPR-FILM AGITATOR;MLE-5000,PET T	-	SNA
-	JC72-10925A	PPR-FILM SUPPORT AGI;MLE-5000,PE	-	SNA
-	JC72-41109A	PMO-AGITATOR;MLE-5000,ABS(GF20%)	-	SNA
-	JC97-01782A	MEA-CHARGE ROLLER;ML-1710,SEC,12*254,0.5	-	SA
-	JC66-00018A	GEAR-CHARGE ROLLER;SF-5100,POM(M	-	SNA
-	JC66-00524A	ROLLER-CHARGE ROLLER;ML-1510,NBR+SBR,1	-	SNA
-	JC97-01783A	MEA-SUS BLADE;ML-1710,SEC,242,SUS+BRACK	-	SNA
-	JC61-00597A	BRACKET-P-BLADE;ML-1400,SECC,1.6,259,10,	-	SNA
-	JC70-00452A	IPR-SUS BLADE;ML-1710,SUS301,0.6,0.08T,1	-	SNA
-	JC97-01789A	MEA UNIT-CLEANING FELT;ML-1710,SAMSUNG	-	SNA
-	JC61-00596A	BRACKET-P-CLEAN;ML-1400,SECC,1.2,259,9,-	-	SNA
-	JC72-00826A	PMO-FILM OPC	-	SNA
-	JC74-00008A	MCT-FUR FOAM CR APO;SF-5100,FUR,	-	SNA
8.1-1 8.5-0	JC96-02710A	ELA HOU-UNIT FRAME_220V;SCX-4114F,LEXM	F2074	SA
-	0201-001183	ADHESIVE-AA;ARON ALPHA #202F,NTR,100,200	-	SNA
-	0205-001003	GREASE-BEARING;NYOGEL788,DAMPING	-	SNA
-	0205-001056	GREASE-GRAPHITE;CRS841,WHT,-	-	SNA
-	0205-001067	GREASE-GRAPHITE;NYOGEL 756G,HYDR	-	SNA
-	6003-000119	SCREW-TAPTITE	-	SA
-	6003-000196	SCREW-TAPTITE;PWH,+ ,B,M3,L10,NI	-	SA
-	6006-001078	SCREW-TAPTITE	-	SNA
-	6031-001051	WASHER-PLAIN;M4,ID4.1,OD7.0,T0.1	-	SNA
8.6-9 8.7-14	6044-000001	RING-CS;ID3,OD3,T0.25,BLACK,SUS304	-	SNA
8.5-23	6107-001162	SPRING-ETC;SUS304-WPB,-,PI0.45,D4.45,L12	-	SA
8.5-52	6107-001164	SPRING-TS	-	SA
8.5-53 8.6-30	6107-001165	SPRING-TS	-	SNA
8.5-45-3	6107-001167	SPRING-CS	-	SA
8.5-40 8.5-47-3	6107-001170	SPRING-TS	-	SA
8.5-43	JC33-00009A	SOLENOID-HB (PICK-UP);-,ML-1510,DC24V,-,	P2162	SA
8.5-44	JC33-00010A	SOLENOID-HB (MANUAL);-,ML-1510,DC24V,-,-	S8014	SA
8.5-55	JC39-00229A	CBF HARNESS-OPC_FUSE;SCX-5312F,WIRE HA	H0023	SA
8.5-32	JC61-00047A	SPRING ETC-TR L HAWK;ML-6060A,SUS 304 WP	-	SA
8.5-1	JC61-00579A	FRAME-M-BASE;ML-1400,VBS(VH-0810P),-,-,B	B0080	SA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
8.5-29	JC61-00583A	HOLDER-PTL;ML-1400,ABS,-,-,BLK,-	H4041	SA
8.5-37	JC61-00585A	BUSH-M-FEED IDLE;ML-1400,POM(M90-44),-,-	F6043	SA
8.5-27-1	JC61-00586A	BUSH-M-PICK_UP L	P2039	SA
8.5-27-6	JC61-00587A	BUSH-M-PICK_UP R;ML-1400,POM(M90-44),-,-	P2067	SA
8.5-31	JC61-00588A	BUSH-M-TR L;ML-1400,POM(M90-44),-,-,BL	K2886	SA
8.5-27-7	JC61-00591A	HOUSING-M-PICK_UP;ML-1400,PC+ABS,-,-,-,N	P2040	SA
8.5-12	JC61-00592A	HOUSING-TERMINAL;ML-1400,ABS,-,-,-,BLK,V	H6040	SA
8.5-27-3	JC61-00593A	STOPPER-PICK_UP;ML-1400,POM(M90-44),-,-,	-	SNA
8.5-4	JC61-00594A	GUIDE-M-TR RIB;ML-1400,PC+ABS,-,-,-,BLK,	G2079	SA
8.5-46	JC61-00602A	BRACKET-P-FEED;ML-1400,SECC,1,-,-,-,-	F6040	SA
8.5-3	JC61-00604A	PLATE-P-SAW;ML-1400,SUS304-CSP,0.15,16,2	P5152	SNA
8.5-2	JC61-00607A	GUIDE-P-TR ;ML-1400,SECC,0.5,241,95,-,-	G2089	SA
8.5-49	JC61-00718A	GUIDE-P-PAPER;ML-1710,SECC,0.8,24.9,262.	G2086	SA
8.5-7	JC61-00836A	FOOT-FRONT;ML-1750,NBR,D7,-,12,-,-	F1011	SA
-	JC61-00937A	GUIDE-M-KNOCK UP;ML-1750,POM,-,60,15,-,-	-	SA
8.5-16	JC61-70932A	SPRING ETC-GUIDE DEVE;ML-5000A,-,D4.5,-,	Z4188	SA
8.5-38	JC61-70958A	SPRING ETC-TR	Z4041	SNA
-	JC63-00291A	SHEET-GUIDE PAPER;ML-1750,PC,0.125T,228,	-	SNA
8.5-41	JC66-00377A	CAM-M-PICK_UP;ML-1400,POM(M90-44),-,-,NT	P2042	SA
8.5-50	JC66-00394A	GEAR-FEED 2;ML-1400,POM(M90-44),-,-,-,NT	F6072	SA
8.5-51 8.7-15	JC66-00396A	GEAR-IDLE 23;ML-1400,POM(M90-44),0.8,23,	G0256	SA
8.5-47-5	JC66-00398A	SHAFT-FEED;ML-1400,POM+GF20%,-,-,-,-	F6210	SA
8.5-27-2	JC66-00399A	SHAFT-P-PICK_UP;ML-1400,SECC,-,-,-,-,0.8	P2160	SA
8.5-24	JC66-00526A	ROLLER-FEED ROLLER 1;ML-1510,SUM24L+EPI	F6201	SA
8.5-36	JC66-00527A	SHAFT-FEED IDLE;ML-1510,SUM24L,225,8,-,-	F6209	SA
8.5-33	JC66-00598A	ROLLER-FEED ;ML-1710,SUM24L+EPDN,3/14.5,	F6200	SA
-	JC66-00671A	DAMPER-SOLENOID;ML-1750,NBR,-,3,20,23,-,	-	SNA
-	JC66-00720A	SHAFT-P-CORE;ML-1750,SECC 1.6T,220,-,-,-	-	SNA
8.5-30	JC67-00027A	LENS-PTL;ML-1400,PC,NTR,-,-,-,-	K3433	SA
-	JC68-00317A	LABEL(R)-HOT CAUTION,KME;ML-7050,TETRON	-	SNA
8.5-22 8.5-28	JC70-00307A	IPR-P-EARTH TRANSFER;ML-1400,SECC,-,1.0T	K3367	SA
8.5-42	JC70-00308A	IPR-P-GROUND_DRIVE;ML-1400,SUS304-CSP,-,	F4106	SNA
-	JC70-00309A	IPR-P-GROUND_EARTH TR;ML-1400,SUS304-CSP		SNA
8.5-35	JC70-00310A	IPR-P-GROUND_FUSER;ML-1400,SUS304-CSP,-	F4105	SNA
8.5-8	JC70-00311A	IPR-P-GROUND_TR;ML-1400,SUS304-CSP,-,0.2	F4104	SNA
8.5-10	JC70-00312A	IPR-P-TERMINAL CON;ML-1400,SUS304-CSP,-,	K3385	SA
8.5-11	JC70-00313A	IPR-P-TERMINAL CR;ML-1400,SUS304-CSP,-,0	K3386	SA
8.5-39	JC70-00335A	IPR-P_GROUND_DRIVE2;ML-1400,SUS304-CSP,	D4060	SA
8.5-54	JC70-00340A	IPR-P-TERMINAL DEVE KEY;SCX-4114F,SUS304	T2116	SNA
8.5-17	JC70-00458A	IPR-P-GROUND_GUIDE PAPER;ML-1710,SUS304	G2285	SNA
8.5-34	JC72-00102A	PMO-BUSHING_TR(L);SF-5100,POM ,B	K3856	SA
8.5-5	JC72-00143A	PMO-GEAR_EXIT_DRV16;SF-5100,POM,	-	SNA
8.5-25	JC72-00382B	PMO-BUSHING FEED;ML-1710,DELIRIN8903,WHI	F6161	SA
8.5-14	JC72-00974A	PMO-ACTUATOR CVR OPEN;ML-1400,ABS,BLK,	O1073	SA
8.5-20	JC72-00975A	PMO-ACTUATOR EMPTY;ML-1400,ABS,BLK,-,-,H	K3816	SA
8.5-19	JC72-00976A	PMO-ACTUATOR FEED;ML-1400,ABS,BLK,-,-,HB	F6156	SA
8.5-21	JC72-00977A	PMO-ACTUATOR MANUAL;ML-1400,ABS,BLK,-,-,	K3817	SA
8.5-45-2	JC72-00979A	PMO-GEAR PICK_UP A;ML-1400,POM(M90-44),N	P6221	SA
8.5-45-1	JC72-00980A	PMO-GEAR PICK_UP B;ML-1400,POM(M90-44),N	P2126	SA
8.5-27-4	JC72-00982A	PMO-IDLE PICK_UP;ML-1400,POM(M90-44),NTR	P2131	SNA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
8.5-13	JC72-00983A	PMO-LOCKER CST;ML-1400,POM,BLK,-,-,-,-,-	L6030	SA
8.5-18	JC72-00984A	PMO-PLATE GUIDE DEVE_L;ML-1400,POM(M90-	G2285	SA
8.5-15	JC72-00985A	PMO-PLATE GUIDE DEVE_R;ML-1400,POM(M90	G2286	SA
8.5-27-5	JC72-01231A	SPONGE-ROLLER PICK_UP;ML-1510,URETHAN	P2164	SA
8.5-9	JC75-00049A	MEC-TERMINAL;SF-5100,SAMSUNG,IVR	K3739	SA
-	JC61-00035A	SPRING-HV APOLLO;SF-5100,SUS304W	-	SNA
-	JC70-00050A	IPR-TERMINAL;SF-5100,SWRCH,4.4,N	-	SNA
8.5-56	JC92-01620B	PBA SUB-PTL;SCX-4100,SEC,-,PTL,-,-,-,9.5	M0248	SA
-	0601-001908	LED;ROUND,RED,3MM,630NM,3.2X4.6MM	-	SNA
-	JC39-00243A	CBF HARNESS-PTL;ML-1710,CBF,UL 1061,2P,1	H1212	SA
-	JC94-00738A	PHANTOM AU JC92-01620B	-	SNA
-	JC41-00171C	PCB-PTL (1LAYER);SCX-4100,FR-1,1,-,1.6T,	-	SNA
8.1-16 8.5-48 8.6-0	JC96-02813A	ELA HOU-FUSER 220V, ROCKY;SCX-4114F,SEC	F4002	SA
-	0105-001032	PAPER-ART;75g,W210,-,WHITE,HANSO	-	SNA
8.6-13	1404-001298	HERMISTOR-NTC;7KOHM,-,3370K,0.3MW/C,-,-	W3071	SA
8.6-20	4713-001183	LAMP-HALOGEN	K2297	SA
-	6003-000196	SCREW-TAPTITE;PWH,+ ,B,M3,L10,NI	-	SA
-	6003-000269	SCREW-TAPTITE;BH,+ ,S,M3,L6,ZPC(Y	F1017	SA
-	6006-001078	SCREW-TAPTITE	-	SNA
-	6006-001193	SCREW-ASSY MACH;WSP,PH,+ ,M3,10,ZPC(YEL	-	SNA
8.6-32	6021-000222	NUT-HEXAGON;2C,M3,ZPC(YEL),SM20C,-	M0006	SNA
-	6031-001051	WASHER-PLAIN;M4,ID4.1,OD7.0,T0.1	-	SNA
8.5-6	6044-000001	RING-CS;ID3,OD3,T0.25,BLACK,SUS304	-	SNA
-	6107-001165	SPRING-TS	-	SNA
8.6-24	6107-001168	SPRING-CS	-	SNA
-	JB75-10028A	MEC-RIBBON	-	SNA
8.6-15	JC39-00238A	CBF HARNESS-FUSER 220V;ML-1710,UL3122 #1	H1087	SA
8.6-6	JC47-00005A	THERMOSTAT-150;ML-1510,-,125/250V,15/7.5	K4279	SA
8.6-3	JC61-00064A	SPRING-CLAW;ML-5200A,SUS 304 WPB	-	SNA
8.6-26	JC61-00581A	HOLDER-ACTUATOR;ML-1400,PC(NH-1023),-,-,	-	SNA
8.6-2	JC61-00584A	HOLDER-M-PLATE CLAW;ML-1400,PET+GF30%,	-	SA
8.6-17	JC61-00589A	BUSH-M-HR L;ML-1400,PPS,-,-,-,-,V0	-	SNA
8.6-19	JC61-00590A	BUSH-M-HR R;ML-1400,PPS(RBA313N, CONDUCT	-	SA
8.6-29	JC61-00595A	GUIDE-M-INPUT;ML-1400,PET+GF30%,-,-,-,BL	-	SNA
8.6-35	JC61-00605A	PLATE-P-CLAW;ML-1400,SUS304-CSP,0.1,-,-,	-	SNA
8.6-5	JC61-70976A	SPRING ETC-FUSER EXIT;- ,SUS304WPB,D2.8,-	S0021	SNA
8.6-1	JC63-00105A	COVER-M-FUSER;ML-1400,PET+GF30%,-,-,-,V0	-	SNA
8.6-34	JC63-00244A	COVER-M-EXIT LOWER;ML-1750,PET GF 30%,-,	-	SNA
8.6-21	JC66-00380A	ROLLER-M-EXIT F/UP;ML-1400,PC(NH-1023),1	E4159	SA
-	JC66-00396A	GEAR-IDLE 23;ML-1400,POM(M90-44),0.8,23,	G0256	SA
8.6-10	JC66-00397A	GEAR-RDCN 25/15;ML-1400,POM(M90-44),-,25	G0386	SA
8.6-16	JC66-00564A	GEAR-FUSER, Z37;ML-1710,HTN51G35HSL,0.8,	-	SA
8.6-22	JC66-00600A	ROLLER-PRESSURE	P6014	SA
8.6-18	JC66-00601A	ROLLER-HEAT	H2010	SA
8.6-23	JC66-10901A	BEARING-PRESSURE/R;ML-165,PPS,5,-,14.8	-	SA
-	JC68-00407A	LABEL(R)-HV FUSER;ML-6060,PVC,-,220V,-	L0018	SNA
8.6-33	JC68-30928D	LABEL(P)-CAUTION, HOT_FUSER	L0035	SNA
8.6-28	JC70-00317A	IPR-P-FRAME_FUSER;ML-1400,SECC,-,1.2,356	-	SNA
8.6-14	JC70-00449A	ELECTRODE-WIRE_R;ML-1510,-,-,-,-,-	-	SA
8.6-12	JC70-00450A	ELECTRODE-WIRE_L;ML-1510,-,-,-,-,-	-	SA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
8.6-11	JC70-00466A	ELECTRODE-LAMP2;ML-1750 / ML-1710,-,2,-,	-	SNA
8.6-7	JC72-00143A	PMO-GEAR_EXIT_DRV16;SF-5100,POM,	-	SNA
8.6-25	JC72-00382A	PMO-BUSHING TX;ML-6060A,POM,BLK,-,-	-	SNA
8.6-27	JC72-00987A	PMO-ACTUATOR_EXIT;ML-1400,PC(NH-1023),BL	E4093	SA
8.6-4	JC72-40361A	PMO-ROLLER_EXIT;SCF(XR),POM,NTR,-,-	R0015	SNA
8.6-31	JC73-00017A	RMO-RUBBER_EXIT;SF-5100,EPDM,11.	-	SA
8.5-47	JC97-01788A	MEA UNIT-CLUTCH;ML-1710,SAMSUNG,-,-,-,-,	C9040	SA
-	6107-001171	SPRING-TS	-	SA
8.5-47-1	JC66-00393A	GEAR-FEED 1;ML-1400,POM(M90-44),-,-,-,NT	F6071	SA
8.5-26	JC66-00398A	SHAFT-FEED;ML-1400,POM+GF20%,-,-,-,-,-	F6210	SA
8.5-47-2	JC72-00978A	PMO-COLLAR_SPRING;ML-1400,POM(M90-44),N	Z4125	SA
8.5-47-4	JC72-00981A	PMO-HUB CLUTCH;ML-1400,POM(M90-44),NTR,-,	-	SNA
8.1-3	JC96-02733A	ELA UNIT-RX DRIVE;ML-1710/ML-1750,SAMSUN	D4033	SA
-	0205-000005	GREASE-BEARING;EP56,-,-	-	SNA
-	6001-000131	SCREW-MACHINE;BH,+ ,M3,L6,ZPC(YEL	-	SNA
-	6031-000023	WASHER-PLAIN;- ,ID5.9,OD10.0,T0.5	-	SNA
-	JC31-00028A	MOTOR STEP-HUMMINGBIRD	M2159	SA
-	JC61-00598A	BRACKET-P-GEAR 1400;ML-1400,SECC,1.6,190	B4025	SA
-	JC61-00599A	BRACKET-P-MOTOR 1400;ML-1400,SECC,1.6,60	B4025	SNA
-	JC66-00388A	GEAR-RDCN 53/26;ML-1400,POM(M90-44),-,53	G0393	SA
-	JC66-00389A	GEAR-RDCN 57/18;ML-1400,POM(M90-44),-,57	G0394	SA
-	JC66-00390A	GEAR-RDCN 103/41;ML-1400,POM(NW-02),-,10	G0396	SA
-	JC66-00391A	GEAR-RDCN 113/33;ML-1400,POM(NW-02),-,11	G0381	SA
-	JC66-00392A	GEAR-RDCN 90/31;ML-1400,POM(M90-44),-,90	G0380	SA
-	JC72-00825A	PMO-IMPELLER_DRV	-	SNA
-	JC96-02953A	ELA HOU-COVER;SF-565P,SEC,- ,COVER ASS'Y,	-	SNA
-	6003-000196	SCREW-TAPTITE;PWH,+ ,B,M3,L10,NI	-	SA
8.1-10	JC63-00320A	COVER-M_SIDE R;SF-565P,HIPS,2.5,290.0,26	-	SA
8.1-11	JC96-02974A	ELA HOU-COVER SIDE L;SF-565P,SEC,- ,SIDE	Z2269	SA
8.1-11-2	3001-001494	SPEAKER;1W,8OHM,83DB,500HZ	-	SA
-	6003-000264	SCREW-TAPTITE	-	SNA
8.1-11-3	GB70-10500A	IPR-UNIT FIXING BRAC	-	DNA
8.1-11-1	JC63-00319A	COVER-M_SIDE L;SF-565P,HIPS,2.5,290.0,26	-	SNA
8.1-9	JC97-01746K	MEA UNIT-COVER FRONT;SF-565P,SEC,- ,OPEN	Z2409	SA
-	6003-000264	SCREW-TAPTITE	-	SNA
8.1-9-3	JC63-00103H	COVER-M_FRONT;SF-565P,HIPS,2.5,320.6,157	-	SNA
8.1-9-5	JC66-00387A	GEAR-RACK_PINION;ML-1400,POM(M90-44),-,-	G0378	SA
-	JC68-01085F	LABEL(P)-EXTRACT;SF-560,SAMSUNG,ART1000	-	SNA
8.1-9-4	JC70-00302F	ADJUST-M_MANUAL L;SF-565P,HIPS,2.5,33.9,	K2008	SA
8.1-9-1	JC70-00303F	ADJUST-M_MANUAL R;SF-565P,HIPS,2.5,33.9,	K2009	SA
8.1-9-2	JC70-00304A	ADJUST RACK-M-MANUAL;ML-1400,POM(M90-4	K2007	SA
8.1-2	JC97-01854A	MEA UNIT-COVER EXIT;SF-565P,SEC,- ,EXIT C	Z2408	SA
8.7-0	-	-	-	-
-	0205-001003	GREASE-BEARING;NYOGEL788,DAMPING	-	SNA
-	6031-001051	WASHER-PLAIN;I4,ID4.1,OD7.0,T0.1	-	SNA
-	6044-000001	RING-CS;ID3,OD3,T0.25,BLACK,SUS304	-	SNA
8.7-12	6107-001163	SPRING-CS;SUS304-WPB,- ,PI0.4,D3.9,L13,-,	-	SA
-	JC61-00582A	HOLDER-M-EXIT F/DOWN;ML-1400,PC(NH-1023)	H4026	SA
8.7-6	JC61-00829A	HOLDER-BEARING EXIT F/DOWN;SCX-4216F,PC	H4009	SA
8.7-9	-	-	-	-
8.7-1	JC63-00322A	COVER-M_EXIT;SF-565P,HIPS,2.5,330.0,135.	-	SNA
8.7-7	JC66-00038A	GEAR-EXIT F/DOWN;ML-4500,POM,WHT	E4039	SA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
8.7-2	JC66-00378A	ROLLER-EXIT F/DOWN;ML-1400,PC(NH-1023),1	E4159	SA
8.6-8	JC66-00396A	GEAR-IDLE 23;ML-1400,POM(M90-44),0.8,23,	G0256	SA
8.7-4	JC66-00626A	ROLLER-M_DECURL;SCX-4114F,POM,D14.4,-,W	K4219	SA
8.7-8	JC66-10201A	BEARING-EXIT FU;ML-80,POM,-,-,-	B1015	SA
8.7-13	JC72-00143A	PMO-GEAR_EXIT_DRV16;SF-5100,POM,	-	SNA
8.7-10	JC72-41081B	PMO-M-ROLLER EXIT_MAIN 5;ML-1710,POM, 50	-	SNA
8.7-11	JC72-41082B	PMO-M-ROLLER EXIT_FR 500;ML-1710,POM, 50	-	SNA
8.7-3	JC73-40915A	RMO-RUBBER EXIT	E4155	SA
8.1-12	JC97-01855A	MEA UNIT-COVER REAR;SF-565P,SEC,-,COVER	Z2421	SA
8.1-12-2	JC63-00142D	COVER-M_FACE UP;SF-565P,ABS,2.5,244.6,85	Z2142	SA
8.1-12-1	JC63-00321A	COVER-M_REAR;SF-565P,HIPS,2.5,320.0,280.	-	SNA
-	JC96-02954A	ELA HOU-ENGINE;SF-565P,SEC,-,ENGINE ASS'	-	SNA
-	6001-000568	SCREW-MACHINE;PH,+ ,M3,L8,NI PLT,	-	SA
-	6003-000119	SCREW-TAPTITE	-	SA
-	6003-000196	SCREW-TAPTITE;PWH,+ ,B,M3,L10,NI	-	SA
-	6003-000266	SCREW-TAPTITE	-	SNA
-	6003-000301	SCREW-TAPTITE;BH,+ ,S,M4,L6,ZPC(YEL),SWRC	-	SNA
8.1-24	6103-001048	SUPPORTER;DASS-T20N,L37.1,NTR,NYLON6/6	-	SA
8.1-13	JC31-00027A	FAN-DC_HUMMINGBIRD	F5019	SA
-	JC39-00090A	CBF HARNESS-DUPLEX GND	-	SA
8.1-20	JC39-00240B	CBF HARNESS-ENGINE	H1070	SA
-	JC39-00241A	CBF HARNESS-MOTOR	M2053	SA
8.1-5	JC39-00242A	CBF HARNESS-LSU	L7002	SA
8.1-23	JC39-00317A	CBF SIGNAL-LIU FFC	-	SNA
-	JC61-00606A	PLATE-P-CHANNEL;ML-1400,SECC,1,-,-,-	P5151	SA
8.1-18	JC61-00693A	BRACKET-P-INLET, ROCKY;SCX-4114F,SECC,T0	B4027	SA
8.1-14-3	JC66-00395A	GEAR-TRANSFER;ML-1400,POM(M90-44),-,-,-,	G0448	SA
8.1-14-1	JC66-00528A	ROLLER-TRANSFER ROLLER;ML-1510,NBR+EC	T3014	SA
8.1-14-2	JC72-00851A	PPR-SPACER TR	-	SNA
8.1-27	JC92-01570A	PBA SUB-HOOK;SF-565P,USA,USA,HOOK PBA,-	-	SA
-	3409-001094	SWITCH-HOOK;48V,200MA,DPDT,1.2MM	-	SA
-	3722-001322	JACK-MODULAR;4P/4C,-,N,STRAIGHT,-,N,WHT,	-	SNA
8.1-28	JC39-00311A	CBF HARNESS-HOOK;SF-565P,WIRE HARNESS	-	SNA
-	JC41-00227A	PCB-HOOK;SF-565P,FR-1,1L,V1.0,1.6T,58MMX	-	SNA
8.1-17	JC97-01794A	MEA UNIT-SHIELD ENGINE;SCX-4114F,SAMSUN	E2098	SA
8.1-17-2	6103-001056	SUPPORTER;DASC-8N,L11,NATUAL,NYLON 6/6	-	SNA
8.1-17-1	JC63-00144A	SHIELD-ENGINE, ROCKY;SCX-4114F,SECC,T0.8	E2107	SA
8.1-6	JC96-02976A	ELA HOU-SCAN;SF-565P,SEC,-,SCAN ,ASS'Y,-	K3030	SA
-	0105-001032	PAPER-ART;75g,W210,-,WHITE,HANSO	-	SNA
-	0203-000007	TAPE-FILAMENT;3M,T0.15,W18,L55M,	-	SNA
-	6003-000196	SCREW-TAPTITE;PWH,+ ,B,M3,L10,NI	-	SA
-	6501-000004	CABLE TIE;DA-80,T1,W2.5,L80,NTR,	-	SA
-	JC39-00312A	CBF HARNESS-CIS;SF-565P,WIRE HARNESS,UI	-	SNA
-	JC39-00323A	CBF HARNESS-MOTOR;SF-565P,WIRE HARNES	-	SA
8.1-6-1 8.2-0	JC96-02950A	ELA HOU-COVER TOP;SF-565P,SEC,-,COVER T	-	SA
-	0205-001056	GREASE-GRAPHITE;CRS841,WHT,-	-	SNA
8.2-17	0609-001174	CONTACT IMAGE SENSOR	-	SA
-	6003-000196	SCREW-TAPTITE;PWH,+ ,B,M3,L10,NI	-	SA
-	6003-000264	SCREW-TAPTITE	-	SNA
8.2-8	6107-001224	SPRING-TS;SUS304WPB,-,PI0.95,-,-,-,ID6	-	SA
8.2-19	JB61-00137A	GUIDE-M_CIS R;SF-330,POM,T1.5,W44,L32.5,	G2309	SA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
8.2-18	JB61-00138A	GUIDE-M_CIS L;SF-330,POM,T1.5,W44,L32.5,	G2308	SA
8.2-20	JB61-70938A	SPRING-CIS(ATLAS);SF3000,SUS304W	L5001	SA
8.2-14	JB66-00126A	GEAR-PINION SSI;MJC-3700,POM,0.7,18,12.6	-	SNA
8.2-10	JB66-00204A	SHAFT-M_EXIT 21;SF-452,POM,-,14,-,-,-	S4113	SA
8.2-5-3	JB75-00052A	MEC-ROLLER ADF;SF-3100,SEUK,NTR	A2013	SA
8.2-5-2	JB72-00136A	PMO-SLEEVE ADF;SF-3100,POM,NTR,9	-	SNA
-	JB97-01207A	MEA ETC-ROLLER WHITE;SF-3100,SEU	Z6238	SA
-	0205-001056	GREASE-GRAPHITE;CRS841,WHT,-	-	SNA
-	JB66-00004A	GEAR-DRIVE;SF-3100,POM,WHT,0.6,2	G2300	SNA
-	JB72-00137A	PMO-BUSHING WHITE;SF-3100,POM,WH	B6030	SA
8.2-15	JB75-00053A	MEC-ROLLER WHITE;SF-3100,SEUK,WH	-	SNA
8.2-12	JC61-00858A	GUIDE-M_DOC L;SF-565P,HIPS,2.5,126.8,38.	-	SA
8.2-13	JC61-00859A	GUIDE-M_DOC R;SF-565P,HIPS,2.5,126.8,38.	-	SA
8.2-7	JC61-00865A	PLATE-P_GROUND CIS;SF-565P,PHOSPHOR BF	-	SNA
8.2-1	JC63-00323A	COVER-M_TOP;SF-565P,HIPS,2.5,286.2,356.2	-	SA
8.2-5-1	JC66-00680A	SHAFT-M_DRIVER ADF;SF-565P,ACETAL,98.1,5	-	SNA
8.2-11	JC66-00681A	LINK-M_SCAN OPEN;SF-565P,ACETAL,59.2,2.5	-	SNA
8.2-6	JC72-00387A	PMO-BUSHING_F/DOWN;ML-6060A,POM,BLK,-,-	K3854	SA
8.2-2	JC72-00973A	PMO-STACKER_RX;ML-1400,ABS,BLUE,-,-,V0,-	Z5090	SA
8.2-16	JC72-41191A	PMO-BEARING SHAFT;ML-6000,POM,WHT,HB,-	S4068	SA
8.2-3	JC96-02949A	ELA HOU-SCAN MOTOR;SF-565P,SEC,-,SCAN M	M2166	SA
-	6002-000175	SCREW-TAPPING;PH,+,2,M3,L8,ZPC(Y	-	SNA
-	6003-000269	SCREW-TAPTITE;BH,+,S,M3,L6,ZPC(Y	F1017	SA
-	JB61-00140A	GUIDE-M_SWING;SF-330,POM,T1.2,W33,L10.4,	-	SNA
-	JB61-70922A	SPRING ETC-CLUTCH	C9078	SA
-	JB66-00005A	GEAR-TRANS;SF-3100,POM,WHT,0.6,3	G2307	SNA
-	JB66-00006A	GEAR-IDLE;SF-3100,POM,WHT,0.6,20	G0279	SNA
-	JB66-00212A	GEAR-M_IDLE20;SF-452,POM(DELIN 500P),0.6	-	SNA
8.2-4	JC31-00032A	MOTOR STEP-TX;SP-42HD-120M,SF-565P,0.2A,	M2166	SA
-	JC61-00862A	BRACKET-P_TX;SF-565P,SECC,T1.2,79.5,66.5	-	SNA
-	JC61-00863A	BRACKET-M_TX;SF-565P,PC+GF10%,2.5,79.5,6	-	SNA
-	JF72-41293A	PMO-GEAR CLUTCH;SF1600,POM,NTR+W	C9066	SNA
-	JF72-41300A	PMO-GEAR DEACC(1);SF1600,POM,NTR	R1105	SNA
8.2-21	JC97-01865A	MEA UNIT-CHUTE;SF-565P,SEC,-,CHUTE ASS'Y	-	SA
8.2-21-1	JC61-00860A	CHUTE-M_A;SF-565P,HIPS,IVORY,106.2,-,2.5	-	SNA
8.2-21-2	JC61-00861A	CHUTE-M_B;SF-565P,HIPS,IVORY,106.0,-,2.5	-	SNA
8.2-9	JG72-40744A	PMO-BUSHING TX(B4);CF5700,POM,NTR+WHT(	-	SA
8.1-6-2 8.3-0	JC96-02952A	ELA HOU-OPE;SF-565P,SEC,-,OPE ASS'Y,MFP,	-	SA
-	6003-000196	SCREW-TAPTITE;PWH,+,B,M3,L10,NI	-	SA
8.3-7	JB72-00107B	PMO-KEY STOP;SF-3100,HIPS,ICE ORANGE,PI	K0216	SA
-	JC63-00076A	COVER-WINDOW SF-530;SF-530,PVC FILM,T0.	Z2247	SA
8.3-1	JC63-00326A	COVER-M_OPE;SF-565P,HIPS,2.5,272.5,136.0	-	SNA
8.3-3	JC63-00328A	SHEET-ONE TOUCH;SF-565P,PC SHEET,T0.38,5	-	SNA
8.3-10	JC64-00053A	KEY-M-TEL;SCX-4114F,HIPS,-,HB,IV21,-,-	K0062	SA
8.3-9	JC64-00056A	KEY-M-SCROLL;SCX-4114F,HIPS,-,HB,IV21,-,	K0050	SA
8.3-11	JC64-00058A	KEY-M-TONER SAVE;SCX-4114F,ACRYL,-,HB,CL	K0068	SNA
8.3-12	JC64-00060A	KEY-M-FAX;SCX-4114F,HIPS,-,HB,IV21,-,-	K0038	SA
8.3-6	JC64-00112A	KEY-M_COPY;SF-565P,HIPS,16*79.0*19.0,HB,	-	SNA
8.3-5	JC64-00113A	KEY-M_ONE TOUCH;SF-565P,HIPS,59.0*84.0*1	-	SNA
8.3-8	JC64-00114A	KEY-M_START;SF-565P,HIPS,D29.0,HB,IVORY,	-	SNA
8.3-13	JC64-00115A	KEY-M_SHIFT;SF-565P,HIPS,D14.0,HB,IVORY,	-	SNA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
8.3-4	JC68-01221A	LABEL(P)-ONE TOUCH;SF-565P,SEC,ART 120G,	-	SNA
8.3-2	JC72-00672A	PCT-LCD WINDOW;SF-535E,PC SHEET T0.38,-,	-	SNA
8.3-15	JC73-00171A	RUBBER-TEL;SF-565P,SILICON,159.0*104.0,-	-	SNA
8.3-14	JC73-00172A	RUBBER-ONE TOUCH;SF-565P,SILICON,99.0*89	-	SNA
-	JC96-03059A	ELA UNIT-OPE_LOW;SF-565P NIKE2_LOW,USA,	K3162	SA
8.3-16	JC92-01558A	PBA SUB-LOW_OPE;SF-565P,SEC,KOREA,OPE,	-	SA
-	0604-001154	PHOTO-INTERRUPTER;TR,0.2-1.0MA,8	-	SA
-	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,TP,1608	-	SA
8.3-17	JC39-00310A	CBF HARNESS-OPE;SF-565P,WIRE HARNESS,U	-	SNA
-	JC94-00627A	PHANTOM AU JC92-01558A	-	SNA
-	0401-000116	DIODE-SWITCHING;MMSD914T1,100V,200mA,S	-	SNA
-	0501-000279	TR-SMALL SIGNAL;KSA1182-Y,PNP,150mW,SOT	-	SA
-	0601-001444	LED;CHIP,GRN,1mm,560nm	-	SNA
-	0801-001090	IC-CMOS LOGIC	-	SA
-	2007-000033	R-CHIP;0ohm,5%,1/4W,TP,3216	-	SA
-	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000090	R-CHIP;10Kohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000120	R-CHIP;680ohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000134	R-CHIP;33Kohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000643	R-CHIP;270ohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000729	R-CHIP;300ohm,5%,1/16W,DA,TP,160	-	SA
-	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,	-	SA
-	2203-000626	C-CERAMIC,CHIP;0.022nF,5%,50V,NP	-	SA
-	2203-000998	C-CERAMIC,CHIP;0.047nF,5%,50V,NP	-	SA
-	2404-000284	C-TA,CHIP;10uF,20%,16V,-,TP,3528	-	SA
-	2802-001069	RESONATOR-CERAMIC;7.37MHz,0.5%,T	-	SNA
-	JB13-00004A	IC ASIC-OPE;SF-3100,HT48C5,SSOP,	-	SA
-	JC41-00222A	PCB-LOE_OPE;SF-565P,FR-1,1L,V1.0,1.6T,25	O1069	SNA
-	JC96-03053A	ELA UNIT-LCD UNIT;SF-755P,SEC,LCD UNIT,-	L3011	SA
-	JC39-00230A	CBF HARNESS-LCD;SCX-5312,WIRE,UL2877,14,	-	SNA
-	JG07-20001A	LCD	L3015	SA
8.4-0	JC97-01857A	MEA UNIT-SCAN UPPER;SF-565P,SEC,-,SCAN U	-	SA
-	6003-000264	SCREW-TAPTITE	-	SNA
8.4-6	JB61-00084A	SPRING ETC-ADF;SF-4755,SEP-B,##0.4,##3.0	Z4134	SA
8.4-4	JB61-00107A	OPRING ETC-LEVER SENSOR;SF-430,SUS304,0	Z4209	SA
8.4-5	JB66-00219A	LEVER-M_SENSOR DOC;SF-452,ABS,1.6,18.1,2	S3060	SA
8.4-3	JC39-00319A	CBF HARNESS-SCAN GND;SF-565P,-,UL1007,-,	-	SNA
8.4-1	JC61-00864A	FRAME-M_SCAN UPPER;SF-565P,HIPS,-,HB,IVC	-	SA
-	JC61-70911A	SPRING ETC-EXIT ROLL FD;ML-165,SUS304 WP	-	SA
-	JC63-00359B	SHEET-GUIDE PAPER;SF-565P,PET,T0.188,18.	-	SA
8.4-9	JC66-00558A	SHAFT-IDLE FEED;SCX-4114F,SUM24L,60,2.5,	F6212	SA
-	JC66-00682A	LEVER-M_SENSOR SCAN;SF-565P,ABS,1.5,11.0	-	SA
8.4-13	JC67-00055A	BRUSH-ANTISTATIC 531P;SF-531P,AL+THUNDE	-	SA
8.4-2	JC72-41398A	PMO-LOCKER_MP;ML-6100,POM,NTR,V0,-	L6048	SA
8.4-7				
8.4-11	JC73-00032A	RPR-RUBBER ADF;SF-5100,SILICON,28.6*39.2	K4249	SA
8.4-8	JG72-40043A	PMO-SUPPORT ADF;SF4000,POM,WHT,V	Z7018	SA
8.4-12	JG72-40044A	PMO-HOLDER RUBBER;SF4000,POM,WHT	H4107	SA
8.4-10	JG72-40663A	PMO-ROLL PINCH;SF5500,POM,BLK,HB,-	P4013	SA
-	JF68-10532B	LABEL(P)-BAR CODE	-	SNA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
8.1-15 8.8-0	JC97-01750E	MEA UNIT-CASSETTE;SF-565P,SEC,-,CASSETT	C4016	SA
-	6003-000261	SCREW-TAPTITE	-	SNA
-	6003-000264	SCREW-TAPTITE	-	SNA
8.8-9	6107-001047	SPRING-ES;PI0.45,D2.75,L24.2,-,SUS304	-	SA
8.8-5	6107-001166	SPRING-CS	-	SA
8.8-1	JC61-00578D	FRAME-M CASSETTE;ML-1710/XRX,HIPS(HR-13	C4008	SA
8.8-6	JC61-00580A	HOLDER-M-PAD;ML-1400,PC(NH-1023),-,,-,-	H4029	SA
8.8-4	JC61-00603A	PLATE-P-KNOCK UP;ML-1400,SECC,1,282,162,	-	SNA
8.8-2	JC61-00918B	GUIDE-M-EXTENSION L2;ML-2250,HIPS,-,150,	E5013	SNA
8.4-14 8.8-7	JC61-70911A	SPRING ETC-EXIT ROLL FD;ML-165,SUS304 WP	-	SA
-	JC63-00290A	SHEET-HOLDER PAD;ML-1750,PC,0.178T,50,28	-	SNA
8.8-15	JC64-00040F	INDICATOR-M LEVER;SF-565P,HIPS,-,GRAY,HB	L4029	SA
8.8-8	JC66-00529A	ROLLER-M-IDLE FEED;ML-1510,POM,13,13,-,-	F6203	SA
-	JC66-00719A	CAM-M-KNOCK UP;ML-1750,POM(M90-44),-,N	-	SNA
8.8-12	JC70-00300A	ADJUST-M-CASSETTE L;ML-1400,ABS,-,-,BL	K2014	SA
8.8-13	JC70-00301A	ADJUST-M-CASSETTE R;ML-1400,ABS,-,-,BL	K2015	SA
8.8-17	JC70-00314A	IPR-PLATE PAD;ML-1400,SUS304-CSP,-,0.1,-	P0009	SA
8.8-3	JC72-00971A	PMO-EXTENSION SMALL;ML-1400,HIPS(HR-136	E5014	SA
8.8-10	JC72-00972A	PMO-PLATE LOCKER;ML-1400,POM(M90-44),W	L6051	SA
8.8-16	JC73-00140A	RPR-FRICTION PAD;ML-1510,NBB,1T 10*45,60	P0034	SA
8.8-18	JC73-00141A	RPR-PAD CASSETTE;ML-1510,NBB,1T 10*45,52	-	SNA
8.8-11	JG61-70531A	SPRING ETC-LOCKER,PLATE	Z4215	SA
8.8-14	JG66-40003A	GEAR-PINION;SF4000,POM,WHT,M1,Z1	G0369	SA
8.1-25	JC97-01858A	MEA UNIT-CRADLE;SF-565P,SEC,-,CRADLE,ASS	K3553	SA
-	0205-001056	GREASE-GRAPHITE;CRS841,WHT,-	-	SNA
-	6003-000196	SCREW-TAPTITE;PWH,+ ,B,M3,L10,NI	-	SA
-	6902-000340	BAG PE	-	SNA
-	JC61-00022A	SPRING ETC-HOOK;SF-5100,SWD,0.26,-,17,17	-	SNA
-	JC72-00127C	PMO-BUTTON HOOK;SF-565P,HIPS,M.GRAY,-,H	-	SNA
-	JC72-00132C	PMO-CRADLE LOWER;SF-565P,HIPS,M.GRAY,-,	-	SNA
-	JC72-00134C	PMO-CRADLE UPPER;SF-565P,HIPS,M.GRAY,-,H	-	SNA
-	JC72-00135A	PMO-SLIDE HOOK;SF-5100,HIPS,LIGHT GRAY,9	-	SNA
-	JC99-01698U	INA-ACCESSORY(ETS)	-	SNA
-	6902-000183	BAG PE;LDPE,T0.05,W350,L400,TRP,8,2-	-	SA
-	JC39-00130A	POWER CODE	K2903	SA
-	JC46-00204A	S/W APPLICATION-DRIVER CD;- ,SF-565P,PRT	-	SNA
-	JC68-01427A	MANUAL-USER GUIDE	-	SNA
8.1-8	JC97-01856A	MEA UNIT-STACKER;SF-565P,SEC,-,STACKER,A	-	SA
-	6902-000286	BAG PE	-	SNA
8.1-8-1	JC63-00324A	TRAY-M STACKER TX A;SF-565P,ABS,2.5,240.	-	SNA
8.1-8-2	JC63-00325A	TRAY-M STACKER TX B;SF-565P,ABS,2.5,110.	-	SNA
-	JF39-50054A	CBF-LINE CORD	H1281	SA
-	JF68-10532B	LABEL(P)-BAR CODE	-	SNA
-	JC99-01700A	PAA WOOD-PACKING(XAA);SF-560/XAA,SEA,-,P	-	SNA
-	0203-001100	TAPE-OPP MASKING;OPP/W75/CLR,T0.	-	SNA
-	6902-000312	BAG PE;HDPE,T0.02,W1000,L900,TRP,8,4-	-	SNA
-	JC69-00503A	CUSHION-SET L/R;SF-565P,EPS,-,-,-,-,WH	-	SNA
-	0105-000101	PAPER-ART;75G,W216,-,-,XEROX3R20	-	SNA
-	JC99-01701U	PAA WOOD-LABEL(ETS)	-	SNA
-	JB68-00792B	LABEL(P)-PTT(BOX);SF-330,ETS,ART PAPER ,	L0134	SA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
-	JB68-00816A	LABEL(P)-TEL NO.(SET);SF-330,ETS,-,-,64,	-	SNA
-	JB75-10029A	MEC-RIBBON	-	SNA
-	JC68-01266A	LABEL(R)-RATING;SF-560,SAMSUNG,MAT,0.025	-	SNA
-	JC68-10932B	LABEL(P)-BLANK(YELLOW);ML-1710,-,ART,100	-	SNA
-	JF68-10532B	LABEL(P)-BAR CODE	-	SNA
-	JC99-01731A	PAA WOOD-MATERIAL;SF-565P,SEC,-,MATERIA	-	SNA
-	0203-000007	TAPE-FILAMENT;3M,T0.15,W18,L55M,	-	SNA
-	JG68-10565A	LABEL(P)-SHEET PAPER;SF5500,MOJ,140X110,	-	SNA
-	0105-001032	PAPER-ART;75g,W210,-,WHITE,HANSO	-	SNA
8.1-19	JC44-00063A	SMPS-POWER PBA(V2)_CHINA;SF-565P,*,AC/DC	M0466	SA
8.1-4	JC59-00018A	UNIT-HUMMINGBIRD LSU;ML-1400,-,-,600DPI,	L7043	SA
-	JC68-01254A	MANUAL INSTALL-QRG;SF-565P,XAA,XEU,ENG,	-	SNA
-	JC69-00505B	BOX(P)-MAIN(XEU);SF-565P/XEU,SW,A-1,492,	-	SNA
8.1-21	JC92-01576A	PBA MAIN-NIKE2_LOW;SF-565P,USA,USA,16PP	M0232	SA
-	0105-000101	PAPER-ART;75G,W216,-,-,XEROX3R20	-	SNA
-	0105-001032	PAPER-ART;75g,W210,-,WHITE,HANSO	-	SNA
-	0202-000008	SOLDER-WIRE;HI-FLO,3.0,-,D3.0,63SN/37PB,	-	SNA
-	0202-000118	SOLDER-WIRE;KR-19 RMA,-,D0.8,-,-	-	SNA
-	0202-001025	SOLDER-WIRE FLUX;KS-611,-,-,-,spray	-	SNA
-	0203-001235	TAPE-PAPER;YW-692,T0.15,W5.8,L4000M,-	-	SNA
-	0203-001236	TAPE-PAPER;YW-4620,T0.12,W6.2,L4000M,-	-	SNA
-	0204-000469	THINNER;#4662,-,0.795,-	-	SNA
-	0402-000129	DIODE-RECTIFIER;1N4003,200V,1A,D	-	SA
-	0403-001440	DIODE-ZENER,1N5956BRL/BZY97-C200,5%,1500	-	SNA
-	0502-000245	TR-POWER;KSB1151-Y,PNP,1.3W,TO-126,-,16	-	SNA
-	0506-001019	TR-ARRAY,STA471A,NPN,4,4W,SIP-10,ST,200	-	SA
-	1203-000429	IC-POSI.FIXED REG.;78L05A,TO-92,3P,-,PLA	-	SA
-	2001-000841	R-CARBON;51OHM,5%,1/4W,AA,TP,2.4X6.4MM	-	SNA
-	2005-000168	R-WIRE WOUND,NON;0.22ohm,5%,2W,AA,BK,4x	-	DNA
-	2401-000042	C-AL,100uF,20%,16V,GP,TP,6.3x7,5	-	SA
-	2401-001946	C-AL;330uF,20%,50V,GP,TP,10x16,5	-	SA
-	2401-002300	C-AL;47uF,20%,50V,GP,TP,6.3x11,5	-	SA
-	2801-001375	CRYSTAL-UNIT;10MHz,20ppm,28-AAA,	-	SNA
-	2801-003376	CRYSTAL-UNIT:32.768KHZ,5P	-	SNA
-	2801-003960	CRYSTAL-UNIT;28.224MHz,50ppm,28-AAA,18pF	-	SA
-	2801-004257	CRYSTAL-UNIT;14.7456MHZ,50PPM,28-AAA,20P	-	SA
-	3702-000118	CONNECTOR-RIBBON;36P,FEMALE,ANGL	-	SNA
-	3708-001371	CONNECTOR-FPC/FC/PIC;18P,1MM,STR	-	SA
-	3711-002003	CONNECTOR-HEADER;BOX,26P,2R,2mm,	-	SNA
-	3711-002808	CONNECTOR-HEADER	-	SNA
-	3711-002812	CONNECTOR-HEADER;BOX,11P,1R,2mm,STRAI	-	SNA
-	3711-003035	CONNECTOR-HEADER;BOX,14P,2R,2mm,STRAI	-	SA
-	3711-003408	CONNECTOR-HEADER;BOX,2P,1R,2mm,STRAIG	-	SNA
-	3711-003409	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIG	-	SNA
-	3711-003410	CONNECTOR-HEADER;BOX,4P,1R,2mm,STRAIG	-	SNA
-	3711-003969	CONNECTOR-HEADER;BOX,2P,1R,2.5mm,STRA	-	SNA
-	3722-001101	JACK-USB;4P/2C,8.38mm,AU,IVR,#22	-	DNA
-	4302-000126	BATTERY-NICD(2ND);3.6V(1.2Vx3),60mAH,CYL	-	SA
-	JB68-00073A	LABEL(R)-BAR CODE;SF-3000,PY,38X	-	SNA
-	JC68-00573A	LABEL(R)-BARCODE;ML-4500,PET,T0.	-	SNA
-	JC94-00651A	PCB	-	SNA
-	0201-001235	ADHESIVE-TS;DEH-390D,RED,400,-	-	SNA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
-	0202-000108	SOLDER-CREAM;RMA-20-21L,-,20~38 ##,62.8S	-	SNA
-	0401-000116	DIODE-SWITCHING;MMSD914T1,100V,200mA,SC	-	SNA
-	0401-000122	DIODE-SWITCHING	-	SA
-	0404-000112	DIODE-SCHOTTKY;RB420D,25V,100mA,	-	SA
-	0407-000101	DIODE-ARRAY;DA204K,20V,100MA	-	SA
-	0407-000122	DIODE-ARRAY;KDS226,80V,300mA,C2-3,SOT-23	-	SA
-	0501-000150	TR-SMALL SIGNAL;2SA1037,PNP,200mW,SOT-2	-	SA
-	0501-000279	TR-SMALL SIGNAL;KSA1182-Y,PNP,150mW,SOT	-	SA
-	0501-000338	TR-SMALL SIGNAL	-	SNA
-	0501-000457	TR-SMALL SIGNAL;MMBT2222A,NPN,22	-	SA
-	0504-000111	TR-DIGITAL;DTC114YK,NPN,200MW,10K/47K,SC	-	SA
-	0801-000477	IC-CMOS LOGIC	-	SA
-	0801-000794	IC-CMOS LOGIC;7S08,AND GATE,SOT-25,5P,63	-	SA
-	0801-000888	IC-CMOS LOGIC;74HCT04,INVERTER,SOP,14P,1	-	SA
-	0801-002143	IC-CMOS LOGIC;7S32,OR GATE,SOT-2	-	SA
-	0801-002446	IC-CMOS LOGIC;74LCX14,SCHMITT INVERTER,7	-	SNA
-	1001-000170	IC-ANALOG SWITCH;MC14051BD,SPDT CMOS,S	-	SA
-	1001-000171	IC-ANALOG SWITCH	-	SNA
-	1003-001535	IC-MOTOR DRIVER;A3977SLP,TSSOP,28P,9.6X4	-	SNA
-	1006-001224	IC-LINE TRANSCEIVER;74LVX161284,TSSOP,48	-	SA
-	1105-001464	SDRAM	-	SA
-	1107-001286	IC-FLASH MEMORY;29LV160,2Mx8Bit,TSOP,48P	-	SNA
-	1201-000105	IC-AUDIO AMP;34119,SOP,8P,150MIL,SINGLE,	-	SA
-	1201-000167	IC-OP AMP;358,SOP,8P,150MIL,DUAL	-	SNA
-	1202-000164	IC-VOLTAGE COMP.;393,SOP,8P,150MIL,DUAL,	-	SA
-	1203-002220	IC-POSI.ADJUST REG.;LD1117,DPAK,3P,240MI	-	SA
-	1203-002233	IC-RESET;XC61F,SOT-23,3P,-,PLASTIC,0.7/1	-	SNA
-	1205-001896	IC-MODEM;FM336R6719-12,QFP,100P,-,PLASTI	-	SA
-	1205-002258	IC-CLOCK GENERATOR;CY25814SC,SOIC,8P,15	-	SNA
-	1205-002339	IC-CLOCK GENERATOR;CY25811SC,SOIC,8P,15	-	SA
-	2007-000067	R-CHIP;15Kohm,1%,1/16W,DA,TP,1608	-	SA
-	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	-	SA
-	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000076	R-CHIP;330ohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP,1608	-	SA
-	2007-000083	350HIP;3Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,16	-	SA
-	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,16	-	SA
-	2007-000090	R-CHIP;10Kohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000091	R-CHIP;12Kohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000093	R-CHIP;20Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000096	R-CHIP;30Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000098	R-CHIP;56Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000099	R-CHIP;62Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000103	R-CHIP;120Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000104	R-CHIP;150Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000109	R-CHIP;1Mohm,5%,1/16W,DA,TP,1608	-	SA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
-	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000116	R-CHIP;120ohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000123	R-CHIP;1.5Kohm,5%,1/16W,DA,TP,16	-	SA
-	2007-000131	R-CHIP;91Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000132	R-CHIP;180Kohm,5%,1/16W,DA,TP,1608	-	SNA
-	2007-000133	R-CHIP;330Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000134	R-CHIP;33Kohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000136	R-CHIP;300Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000368	R-CHIP;130Kohm,5%,1/16W,DA,TP,1608	-	SNA
-	2007-000402	R-CHIP;150ohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000539	R-CHIP;200ohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000729	R-CHIP;300ohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000965	R-CHIP;5.1Kohm,5%,1/16W,DA,TP,16	-	SA
-	2007-001002	R-CHIP;510ohm,5%,1/10W,TP,1608	-	SA
-	2007-001044	R-CHIP;56ohm,5%,1/16W,DA,TP,1608	-	SNA
-	2007-001068	R-CHIP	-	SA
-	2007-002436	R-CHIP;2.7MOHM,5%,1/16W,DA,TP,1608	-	SNA
-	2007-007004	R-CHIP	-	SA
-	2011-000660	R-NET;1Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	-	SA
-	2011-001011	R-NETWORK;10Kohm,5%,63mW,L,CHIP,8P,TP	-	SNA
-	2011-001094	R-NETWORK;39ohm,5%,63mW,L,CHIP,8	-	SA
-	2011-001334	RC-NETWORK	-	SNA
-	2203-000041	C-CERAMIC,CHIP;0.01NF,0.25PF,50V,C0G,TP,	-	SA
-	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,TP,1608	-	SA
-	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,	-	SA
-	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,	-	SA
-	2203-000384	C-CERAMIC,CHIP;0.015nF,5%,50V,NP0,TP,160	-	SA
-	2203-000426	C-CERAMIC,CHIP;0.018nF,5%,50V,NP0,TP,160	-	SA
-	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,T	-	SA
-	2203-000626	C-CERAMIC,CHIP;0.022nF,5%,50V,NP	-	SA
-	2203-000681	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,160	-	SA
-	2203-000783	C-CERAMIC,CHIP;0.33NF,5%,50V,C0G,TP,1608	-	SA
-	2203-000815	C-CERAMIC,CHIP;0.033nF,5%,50V,NP	-	SA
-	2203-000888	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R	-	SA
-	2203-000998	C-CERAMIC,CHIP;0.047nF,5%,50V,NP	-	SA
-	2203-001408	C-CERAMIC,CHIP;0.27nF,5%,50V,NP0,TP,1608	-	SA
-	2203-001607	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0	-	SA
-	2203-001683	C-CERAMIC,CHIP;0.068nF,5%,50V,NP0,TP,160	-	SA
-	2203-002392	C-CERAMIC,CHIP;220nF,+80-20%,50V	-	SA
-	2203-002398	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,1608	-	SA
-	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608,-	-	SNA
-	2203-005819	C-CER,CHIP;1000NF,+80-20%,16V,Y5V,TP,160	-	SNA
-	2402-000176	C-AL,SMD	-	SA
-	2703-000125	INDUCTOR-SMD;10uH,10%,1.25x2x1.2	-	SNA
-	3301-000317	CORE-FERRITE BEAD;AB,2x1.25x0.9m	-	SA
-	3301-001084	CORE-FERRITE BEAD;AB,600ohm,2x1.25x0.9mm	-	SNA
-	3301-001425	CORE-FERRITE BEAD;AB,120ohm,3.2x1.6x1.1m	-	SNA
-	JC13-00021A	IC ASIC-CHORUS2;S3C46Q0X,SF-531P,208P,+1	-	SA
-	JC41-00207A	PCB-MAIN;SF-565P,FR-4,2L,V1.0,1.6T,210 X	-	SNA
8.1-22	JC92-01578B	PBA SUB-NIKE2_LOW(EU);SF-565P,SEC,EU,LIU	L5106	SA
-	0201-001096	ADHESIVE-HM	-	SNA
-	0202-000008	SOLDER-WIRE;HI-FLO,3.0,-,D3.0,63SN/37PB,	-	SNA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
-	0202-000118	SOLDER-WIRE;KR-19 RMA,-,D0.8,-,-	-	SNA
-	0202-001025	SOLDER-WIRE FLUX;KS-611,-,-,-,spray	-	SNA
-	0204-000469	THINNER;#4662,-,0.795,-	-	SNA
-	0402-000132	DIODE-RECTIFIER,1N4004,400V,1A,DO-41,TP	-	SA
-	0403-000716	DIODE-ZENER;MTZJ4.7B,4.59-4.77V,500MW,DO	-	SNA
-	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,	-	SA
-	0501-000501	KSP92TA;MPSA92,PNP,625mW,TO-92,T	-	SNA
-	0502-000288	TR-POWER;KSD288,NPN,25W,TO-220,-,120-24	-	SNA
-	0604-000118	PHOTO-COUPLER,TR,20-300%,200mW,DIP-4,ST	-	SA
-	0604-000142	PHOTO-COUPLER;TR,-,200mW,DIP-4,ST	-	SA
-	1405-000144	VARISTOR;430V,1250A,14x7.2mm,TP	-	SA
-	1405-000170	VARISTOR,82V,1200A,9x4.1mm,TP	-	SA
-	1405-000226	VARISTOR,-,25A,5mm,TP	-	SA
-	2001-000025	R-CARBON,75OHM,5%,1/4W,AA,TP,2.4X6.4MM	-	SA
-	2001-000027	R-CARBON,100OHM,5%,1/4W,AA,TP,2.4X6.4MM	-	SA
-	2001-000110	R-CARBON,10OHM,5%,1/4W,AA,TP,2.4X6.4MM	-	SA
-	2003-000507	R-METAL OXIDE(S);15Kohm,5%,1W,AA,TP,3.3x	-	SA
-	2004-000284	R-METAL	-	SA
-	2004-001773	R-METAL	-	SNA
-	2301-001308	C-FILM,LEAD-PEF;15NF,10%,400V,BK,10.5X4X	-	SNA
-	2305-000583	C-FILM,LEAD-PEF	-	SA
-	2401-000026	C-AL,3.3UF,20%,50V,GP,TP,5X11,5	-	SA
-	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	-	SA
-	2401-000042	C-AL,100uF,20%,16V,GP,TP,6.3x7,5	-	SA
-	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	-	SNA
-	2401-000603	C-AL,1uF,20%,50V,GP,TP,5x11,5	-	SA
-	2401-001775	C-AL:470NF,20%,50V,GP,TP,4X7,5	-	SA
-	3501-000203	RELAY-MINIATURE;5V,200mW,1A,1FormC,6mS,3	-	SA
-	3708-001371	CONNECTOR-FPC/FC/PIC;18P,1MM,STR	-	SA
-	3711-002807	CONNECTOR-HEADER;BOX,6P,1R,2mm,S	-	SNA
-	3722-000255	JACK-MODULAR;6P/4C,INVERTED,N,ANGLE,ST	-	SA
-	4715-001042	SURGE ABSORBER	-	SNA
-	JB68-00073A	LABEL(R)-BAR CODE;SF-3000,PY,38X	-	SNA
-	JB75-10029A	MEC-RIBBON	-	SNA
-	JC39-40511A	CBF HARNESS;ML-80,JUMPER,AWG22,52mm,S	-	SA
-	JC68-00573A	LABEL(R)-BARCODE;ML-4500,PET,T0.	-	SNA
-	JC94-00650A	PCB	-	SNA
-	0201-001235	ADHESIVE-TS;DEH-390D,RED,400,-	-	SNA
-	0203-001235	TAPE-PAPER;YW-692,T0.15,W5.8,L4000M,-	-	SNA
-	0203-001236	TAPE-PAPER;YW-4620,T0.12,W6.2,L4000M,-	-	SNA
-	0401-000116	DIODE-SWITCHING;MMSD914T1,100V,200mA,SO	-	SNA
-	0407-000122	DIODE-ARRAY;KDS226,80V,300mA,C2-3,SOT-23	-	SA
-	0501-000338	TR-SMALL SIGNAL	-	SNA
-	1001-000171	IC-ANALOG SWITCH	-	SNA
-	1201-000167	IC-OP AMP;358,SOP,8P,150MIL,DUAL	-	SNA
-	2007-000033	R-CHIP;0ohm,5%,1/4W,TP,3216	-	SA
-	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	-	SA
-	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000083	350HIP;3Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,16	-	SA
-	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,16	-	SA
-	2007-000088	R-CHIP;7.5Kohm,5%,1/10W,TP,1608	-	SA

SA : Service Available, SNA : Service not Available

Dwaw# (Section-No.)	Part Code	Description	Location	SNA
-	2007-000091	R-CHIP;12Kohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000096	R-CHIP;30Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000100	5-CHIP;68Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,16	-	SA
-	2007-000103	R-CHIP;120Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000104	R-CHIP;150Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000120	R-CHIP;680ohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000121	R-CHIP;820ohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000122	R-CHIP;1.2Kohm,5%,1/16W,DA,TP,16	-	SA
-	2007-000126	R-CHIP;4.3Kohm,5%,1/16W,DA,TP,1608	-	SNA
-	2007-000131	R-CHIP;91Kohm,5%,1/16W,DA,TP,1608	-	SA
-	2007-000293	R-CHIP	-	SA
-	2007-000539	R-CHIP;200ohm,5%,1/16W,DA,TP,160	-	SA
-	2007-000637	R-CHIP;270Kohm,5%,1/16W,DA,TP,16	-	SA
-	2007-000729	R-CHIP;300ohm,5%,1/16W,DA,TP,160	-	SA
-	2007-001161	R-CHIP;75Kohm,5%,1/16W,DA,TP,1608	-	SNA
-	2007-007507	R-CHIP;2.74Kohm,1%,1/16W,DA,TP,1608	-	SNA
-	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,TP,1608	-	SA
-	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,	-	SA
-	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,	-	SA
-	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,T	-	SA
-	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	-	SA
-	2203-001656	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0	-	SA
-	2203-002115	C-CER,CHIP;68nF,+80-20%,50V,Y5V,BK,1608,	-	SA
-	2203-002398	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,1608	-	SA
-	2203-005819	C-CER,CHIP;1000NF,+80-20%,16V,Y5V,TP,160	-	SNA
-	3301-001084	CORE-FERRITE BEAD;AB,600ohm,2x1.25x0.9mm	-	SNA
-	JC41-00208B	PCB-LOW_RUSSIA;SF-565P,FR-1,1L,V1.0,1.6T	-	SNA
-	JF27-60051A	COIL FILTER,CF5400,60uH,50mOHM,18T	-	SNA
-	JG26-50001A	TRANS-MATCHING;SF6000.-,6	-	SA
8.1-26	JC96-01629F	ELA HOU-HANDSET;SF-565P,SEC,UK,HANDSET	H0009	SA
-	3009-001028	AUDIO-RECEIVER;160+-30OHM,97.5+-	-	SNA
-	6044-000138	RING-OP	R1111	SA
-	6902-000338	BAG SHEET;LDPE,T0.05,W120,L350,TRP,-,--	-	SNA
-	JB39-00026A	CBF HARNESS-HANDSET MODULAR	H0004	SA
-	JB70-00007A	IPR-WEIGHT BALANCE;SF-3100,SECC-	-	SNA
-	JB72-00127H	PMO-HANDSET LOWER;SF-335T,HIPS,M.GRAY,	-	SNA
-	JB72-00535D	PMO-HANDSET UPPER;SF-3100,ABS,WHITE,-,V	-	SNA
-	JB72-00665A	PPR-DUMMY HANDSET(VOL)	D2117	SNA
-	JB73-00024A	RMO-WEIGHT RUBBER	R1082	SNA
-	JF73-40501A	RMO-RUBBER MIC	R1109	SNA
-	JF92-00625A	PBA SUB-ETC MIC	-	DNA
-	0403-000142	DIODE-ZENER,IN4736A	-	SNA
-	2301-000490	4.7nF,5%,100V,TP,5.8*3,1*12.5	-	SNA
-	3003-000103	MIC-CONDENSOR	-	SA
-	JF41-10589A	PCB-H/S MIC	-	SNA
-	JG39-60504A	CBF-CURL CORD;SF6000,4P,300mm,WH	W2000	SA