



Control Panel

Use the illustration below to identify components of the Control Panel. The function of each numbered component is described in the table on the following pages. The only features available for the digital press configuration of the DocuColor 2045/2060 are Job Status and Machine Status.



Figure 8. DocuColor 2045/2060 Control Panel

No.	Name		Function
1	Touch Screen		Displays the choices available for various features and digital press status messages. To make a feature selection, touch the appropriate button on the screen.
2	Features	 	Displays the default screen containing the Basic Features, Added Features, Image Quality, and More tabs.
3	Power Saver	 	Puts the digital press in a standby status, where the Fuser temperature is lowered.
4	Job Status	 	Gives a list and current status of all jobs submitted. You can also hold, release, promote, delete and see the details of each job in the digital press queue.
5	Dual Language	 	Alternates between two programmed languages.
6	Access	 	Password protected. Allows access to the Tools Pathway, the Auditron Administration Pathway and the Technical Key Operator (TKO) Pathway.

No.	Name	Function
7	Machine Status	<p>Gives the status of the Paper Trays, Machine Details, Error Log and Maintenance.</p> <p>Machine Status is where you find the serial number for the DocuColor 2045/2060, the service phone numbers and the meters that show the page count for full color, black and white, oversized and total prints.</p>
		 
8	Review	Displays the choices that have been selected.
		 
9	Help	Additional information useful in completing a task is displayed.
		 
10	Clear All	Clears all programming and returns the digital press to the default settings. Clear Memory cannot be used while printing is in progress.
		 
11	Interrupt	<p>Interrupts the printing in process to allow a priority job to be copied. The Interrupt indicator lamp lights up. Press the Interrupt button after the job is completed to return to printing the previous job.</p> <p>Interrupt cannot be selected while using the Poster feature.</p> <p>While running a job in Interrupt, Define Area in the Document Type/Dark Edges feature cannot be selected. Also, Stored Jobs and Special Features cannot be used while running a job in Interrupt.</p>
		 

No.	Name		Function
12	Pause	 	Press the Pause to stop the printing process.
13	Start	 	Press the Start button to start the printing process.
14	Keypad		Allows you to enter your password and the desired number of copies.
16	C		Press the C (Clear) button to return the selected quantity to 1.

Table 1.