

SB Number:	SB 2J5-003	Creation Date: 26/02/2010
Subject:	Firmware upgrade (Added e-MPS function etc.)	
Model:	FS-6970DN	

Content of changes

Item	Contents
1 MP tray	<p>Phenomenon When the default cassette is set to MP tray the following may occur:</p> <ol style="list-style-type: none"> 1. The indication of paper empty for the MP tray is switched OFF. 2. The "Add paper warning" is indicated, when the standard paper cassette and multi purpose tray are empty. <p>Solution Please use one of the following methods:</p> <ol style="list-style-type: none"> 1. Operation panel: Device Common → Error Handling → Set the MP Tray Empty setting to "OFF" 2. Command center: Basic → Device Defaults → Set the MP Tray Empty setting to "OFF" 3. Prescribe command: !R!MPTE 0;EXIT;(MPTE 1;On)
2 Several e-MPS functions have been added.	<p>The following e-MPS functions have been added:</p> <p>Custom Box, Quick Copy, Print Job Stay, Proof print and Private print. Please see the table below for further details.</p>

Added e-MPS functions

Items	Details	Necessary machine modification
1 Custom Box Quick Copy Print Job stay	It is possible to select specified file or all print.	Install a hard disk in the machine.
2 Proof print Private Print	It is possible to select specified file or all print.	Allocate a part of the machines internal memory as a Ram disk or install a hard disk in the machine.

Firmware

Type	Program No.	Check SUM	Version	Status Date
ENGINE	S2J5_1000004001	edc6	004.001	
SYSTEM	2J5_3000.003.008	45f7	003.008	20/01/2010

Classification	<input type="checkbox"/> Entire stock rework	<input type="checkbox"/> In-field modification at next visit	<input type="checkbox"/> In-field modification by case	<input type="checkbox"/> No modification necessary
Field measure	To implement the above mentioned changes, please upgrade the firmware to the latest version and use the latest printer driver.			

Serial numbers of affected machines

Type	Serial number
FS-6970DN	No production has been planned